





HARTING Industrial Raspberry Pi

CONCEPT



What is an "Industrial" Raspberry Pi?

Normal Raspberry Pis are sold online for US\$50-100. They are PCB board products powered by USB cable, which means they regularly overheat if they are run 24/7. Customers wanted a sturdier version of the Raspberry Pi, which we have dubbed "industrial grade". Our Industrial Raspberry Pis fully utilize Raspberry Pi software and related intellectual assets as found on the Internet while also being able to operate continuously in harsh environments, fulfilling necessary industrial standards.

The Ideal Edge Computer

For edge computing many production engineers have replaced Windows-based industrial PCs with Industrial Raspberry Pis. This often provides significant savings, but in addition, for example, open source software NodeRED can quickly design and deploy complicated data mappings. Using CODESYS, which only costs €50, our Industrial Raspberry Pis can easily communicate with PLCs via Ethernet/IP or EtherCAT. Other benefits include the fact that the custom board on the MICA-R broadens interface options including 4-20mA or IO-Link, which are almost impossible for industrial PCs to handle. For further examples, please refer to our application page.



POWERED BY Raspberry Pi

STM32 Microcontroller and Industrial Raspberry Pi Integration

Inexpensive, European microcontrollers like the Arduino or STM32, which are other main players in the IoT world, can directly drive sensors and actuators with a very fast sampling rate. Major microcontrollers have recently begun to offer a user-friendly programming environment, or integrated development environment (IDE), allowing them to be widely used in electronics classes or high school robot competitions. Our Industrial Raspberry Pi, the MICA-R, has an optional custom board with an ARM-based, high-performance microcontroller, the STM32-F4. Combining I/O processing by the STM32 and complicated data processing and presentation by the Raspberry Pi, the MICA-R can be used in many fields. For example, automated guided vehicles (AGVs) which normally require industrial PCs and PLCs, can be driven only by this MICA-R STM32 CONTROL which costs less than US\$500. In addition, sophisticated open source engineering middleware such as ROS can also run on Industrial Raspberry Pis for decentralized collaborative control of multiple AGVs.

Measurement Innovation Combining MEMS chips and Industrial Raspberry Pis

Microelectromechanical systems (MEMS) are IC chips which integrates mechanical sensor elements. Widely used in mobile phones, home appliances, and cars, MEMS contribute to significant size and cost reduction of sensors. While time-of-flight collision sensors for cars and gyroscopes to detect angles of phones are well known, emerging MEMS technologies included doppler sensors to accurately measure speed and gas sensors which detect specific toxic gases. Both have uses in industrial applications. As both MEMS and the above-mentioned microcontrollers are IC chips, these two are easily combined. For example, our new acceleration sensor with the latest 20kHz MEMS accelerometer can directly connect to a MICA-R STM32 SENSOR without any converters. Combining MEMS sensors, a microcontroller, and an Industrial Raspberry Pi results in a high-end, industrial, economic, IoT measurement system.



HARTING Industrial Raspberry Pi





The Concept of the Industrial Raspberry Pi	
Industrial Raspberry Pi Application Examples	• • • 3
MICA-R4: The Environmentally resistant Industrial Raspberry Pi	
About MICA-R4	• • • 4
MICA-R4 BASIC IP20 Basic model (non-waterproof)	• 5-6
• MICA-R4 BASIC IP65 Basic model (waterproof)	
MICA-R4 BASIC RJ Plus IP20 Digital Input/Output, Analog Input (non-waterproof)	
• MICA-R4 BASIC Plus IP65 Digital Input/Output, Analog Input (waterproof)	
• MICA-R4 USB IP20 with additional 2xUSB (non-waterproof)	13-14
• MICA-R4 USB IP65 with additional 2xUSB (waterproof)	15-16
MICA-R4 GPIO IP20 with GPIO port (non-waterproof)	17-18
• MICA-R4 USB GPIO IP20 with additional 1xUSB + GPIO port (non-waterproof)	19-20
MICA-R DIO IP20 with Digital Input/Output, COM, CAN (non-waterproof)	21-22
MICA-R Multi IO IP20 with Digital Input/Output, Analo Input/Output, COM, CAN, STM32 (non-waterproof)	
MICA-R4 SENSOR for sensor connection (waterproof)	• • 25
Accesories: cables and others	• • 26
Costomization examples · · · · · · · · · · · · · · · · · · ·	•• 27
rMICA: 920MHz sub-GHz wireless communication module	
About rMICA	
• rMICA-master: USB wireless base station (wireless parent)	• • 29
• rMICA-vibration: Wireless sensor box for the acceleration sensor (wireless child)	• • 30
aMICA: Camagua	
sMICA: Sensors • sMICA-ACC: Acceleration sensor	21
• sMICA-CUR: DC current sensor	31
SiviloA-Cort. De current sensor	51
RevPi: Industrial Raspberry Pi for control cabinet	
About RevPi	
Base module RevPi Core S/Connect S	
Base module RevPi Core SE/Connect SE	
• RevPi DIO [Digital Input/Output module]	
• RevPi AIO [Analog Input/Output module]	• • 36
Parinharal aquinment	
Peripheral equipment • USB 2.0 camera	37
Industrial USB hub	•• 38

APPLICATION

Edge computing

In this project, we used the MICA-R + IO-Link custom board to receive the data from sensors in the machine tool peripheral equipment (oil circulation unit) in the manufacturing line and the data from the old NC with only a serial port. It is passed to MT Connect, an XML-based equipment condition monitoring network standardized by . By using the MICA-R custom board, it is possible to directly connect MICA-R with on-site equipment with various interfaces. In addition, the host network connected via Ethernet can be of course industry standard networks such as MT Connect, EUROMAP, and OPC UA, as well as messaging protocols such as MQTT to send data to Microsoft and Amazon cloud services. By using middleware, it can be realized without incurring costs. (Upper model: MICA-R4 IO-Link)



Image processing

You can easily build a tailor-made image recognition system for tens of thousands of yen by connecting an industrial Raspberry Pi MICA-R USB and a USB vision camera. In this project, we will develop a custom application using the open source software OpenCV to meet the image processing needs of the automobile assembly process. Specifically, we have developed programs for diagonal reading of QR codes, position detection, shape recognition, worker detection, and transmission of part position information to robots. Machine learning is necessary for worker detection, etc., because each person has a different physique. (Upper model: MICA-R USB IP20/IP65)




PLC linkage by CODESYS

If you install Germany's largest software PLC CODESYS® on the industrial Raspberry Pi RevPi Core S, you can create a simple PLC with reduced cost. On CODESYS®, control data can be shared with other PLCs via global standard control protocols such as Ethernet/IP, Profinet, and EtherCAT. Control programs can also be written in languages such as ladder and function blocks, which control engineers are good at. In this example, the web-based GUI tool included in the CODESYS® package is used to display the control data shared with the PLC on the graphic screen. Graphic screens created with the CODESYS® Web GUI tool can be displayed directly on a large display via HDMI, and can also be displayed on a PC or tablet with a browser installed.




MEMS sensing

This is an example of motor failure diagnosis and predictive maintenance using the acceleration sensor sMICA-ACC equipped with the latest MEMS chip. The MEMS accelerometer attached to the motor can be directly attached to the industrial Raspberry Pi MICA-R STM 32 SENSOR with built-in microcomputer, or it can be connected to the wireless sensor box rMICA-vibration. In this project, measurement data is sent to the wireless base station rMICA-master attached to the industrial Raspberry Pi MICA-R via 920MHz sub-giga band communication via rMICA-vibration. The raw data received by the MICA-R4 is subjected to mathematical processing such as fast Fourier transform and envelope transform at any time by the open software Scipy on the Raspberry Pi, graph drawing, failure judgment, and data file to the host system (customer's server). send. (Upper model: MICA-R4 SENSOR)



AGV control

In this project, we used the industrial Raspberry Pi MICA-R IO series with a built-in microcomputer to develop a control system for an AGV for transport between processes in a factory. The built-in STM32 microcomputer reads the magnetic sensor that detects the magnetic tape on the floor, the obstacle sensor, and the motor encoder, and generates the speed command output that is sent to the left and right brushless motors. On the other hand, smart cameras and RFID readers that read RFID tags embedded in the floor are connected to the Raspberry Pi side via USB connection and are reflected in the control of the AGV in cooperation with the microcomputer. A dedicated Web GUI is provided for AGV operation and teaching, so it can be performed on the browser of a tablet terminal connected to WiFi. Furthermore, open source middleware ROS™ for robot control is run on Raspberry Pi, and advanced cooperative control of many AGVs is performed via a central ROS application server. (Upper model: MICA-R4 Multi IO)



MICA-R4


Environmentally resistant Industrial Raspberry Pi

MICA-R4 is an industrial Raspberry Pi with a built-in Raspberry Pi Compute Module 4 (CM4) for embedded applications. The robust aluminum chassis functions as a heat sink throughout, providing excellent heat dissipation for stable and continuous operation. It is designed for industrial use with onboard eMMC, no SD card for boot, 24VDC power supply, and a wide temperature range of -20 to 60°C. Basically, programs that run on ordinary Raspberry Pi can be run on the MICA-R4 without modification, making it easy to introduce the MICA-R4 from the development environment to the field. The IP65 dustproof and waterproof model can be installed without a control panel in harsh environments, including outdoors.

More Expandability for Industrial Raspberry Pi

MICA-R4 can be additionally equipped with a custom board with various interfaces required for IoT in manufacturing and a microcontroller required for AD conversion and high-speed sampling of sensor values. The custom board is located on the left side of the MICA-R4 main unit and is internally coupled to the carrier board with Raspberry Pi Compute Module 4. The custom board is powered by either 5.0 VDC or 24 VDC from the carrier board as required.

The front panel has up to four ports of M5/M8/M12 connectors, which are international standard industrial waterproof connectors, to meet the interface specifications of the custom board. In addition, the Gigabit Ethernet ports on the IP20 models use the ix Industrial interface, a new small Ethernet standard.





with additional 2xUSB model waterproof type

BASIC model non-waterproof type


Increased processing power, larger memory capacity, and higher speed

CM4 is a genuine Raspberry Pi for embedded applications, equivalent to the general Raspberry Pi 4B. The high-performance Cortex-A72 processor has been clocked at 1.5GHz, up from 1.2GHz in the previous CM3+, and up to 8GB of LPDDR4 SDRAM is now available. New features such as NVMe storage via an M.2 slot, WWAN expansion*, and Gigabit Ethernet support enable the CM3+ to support more advanced applications than ever before.

 * There is one M.2 slot. NVMe storage (SSD) and WWAN module (LTE) cannot be selected at the same time.

Ideal IoT platform by combining custom boards

The industrial Raspberry Pi is an ideal platform for an edge computer. There are currently five types of custom boards in the lineup, with three interface types (USB, IO-Link, and LAN+Serial) and two STM32 microcontroller types for general-purpose control for accelerometers, AGVs, and other applications. In the future, there is also a need for custom boards with FA analog sensor interface (4-20mA) and NVIDIA® Jetson™ GPU for image processing and machine learning, which will be added to the roadmap. We can also develop new custom boards to meet your unique specifications at a low initial cost.





Picture




Product Specifications

		-				
Processor		Broadcom BCM2711, Quad core @ 1.5GHz				
Memory		RAM4GB, eMMC32GB (Depend on model)				
OS		Raspberry Pi OS				
Interface	Front	1x PWR : Power input, 2-line				
		2x LAN : FLAN 1ch, GLAN 1ch				
		1x OPT*1 : i2c/RS-232/485 selectable				
		1x USB : USB2.0 Host Type-A				
		1x Maintenance :Maintenance port(reserved)				
		[Option]1x WLAN IEEE 802.11 b/g/n/ac, Bluetooth 5.0, BLE				
		[Option]1x LTE(M.2 slot/EM7431)				
	Back	1x USB-C : USB Type-C(eMMC writing only)				
		1x SW : eMMC write switch				
		1x microSD : microSD slot				
	Inter	1x M.2 slot B-key*2, 1x nanoSIM slot				
	nal	1x CSI, 1xGPIO 40p				
LED, Butto	on	P: Power status, A0,1: LAN status				
		Pi: User custom/WD error				
RTC/NVR	AM	BR1225[or CR1225] Backup RTC				
Watchdog		Built-in hardware watchdog				
Power/		BASIC:DC10.7V28.8V/				
Consumpt	ion	12W(incl.USB 500mAx1)				
Temperatu	ıre	Operating Temp.: -2060°C, Storage:-2585°C				
Humidity		Operating Humi.:095%(non-condensing)				
IP grade		IP20				
housing m						
Dimension	ıs	W132 x D87 x H35 mm (excluding protrusions)				
Weight BASIC:Approx.540g						
Vibration/s	hock	IEC 60068-2-6 / IEC 60068-2-27				
EMI		Radiated emissions EN55016-2-3				
EMS		Electrostatic radiation immunity EN 61000-4-2				
		Radio frequency electromagnetic fields EN 61000-4-3				
		Fast transient burst EN 61000-4-4				
		DIN rail mounting, wall mounting(Option)				
*1 The eneed is variable, but Data hit: 8 Parity: N. Stop hit: 1 are fixed						

- *1 The speed is variable, but Data bit: 8, Parity: N, Stop bit: 1 are fixed.
- *2 This is not a full pin connection. USB2.0, PCIe, and SIM are connected.

Details of each part



Features

- Industrial Raspberry Pi 4 (CM4)
- New processor, up to 2x faster than CM3
- Raspberry Pi OS compatible (Ubuntu requres 4GB or more RAM)
- DC12/24V power input
- Wide operating temperature range and high noise resistance
- M8, M5, ix connectors with high vibration resistance and connection reliability
- Robust aluminum die-cast housing
- Supports wall mount and DIN rail mount
- On-board eMMC (SD card is not used for boot)
- microSD slot for data storage
- Internal M.2 slot for SSD and WWAN expansion
- Raspi40p connector for expansion board
- Built-in battery backup RTC
- Highly reliable hardware watchdog

Interface

<Connector pin layout>



E0 connector

[GLAN]

or	Pin	Col.	Signal			
	1	BR	24VDC(V1)			
	2	WH	24VDC(V2)			
	3	BL	0V(V1)			
	4	BK	0V(V2)			
		Signal				

Pin	Signal					
Pin	10/100M	1G				
1	TX+	BI_DA+				
2	TX-	BI_DA-				
3	N.C.	GND				
4	N.C.	BI_DC+				
5	N.C.	BI_DC-				
6	RX+	BI_DB+				
7	RX-	BI_DB-				
8	N.C.	GND				
9	N.C.	BI DD+				

10 N.C

E1 connector [FLAN] M8 A-coded



Signal BR TX+ WH RX+

BI_DD-

OPT connector



*1 pin for power output is no output by default

<LED> <ANT SMA port> [Option]

LED	Sts.	Comments	Type			ANT2	ANT1	ANT0
P(GR)	Off	No power supply	Wired LAN					
	On	Power OK	Wire	Wired LAN+LTE			GNSS	Aux
A0(OR)	Blk	E0 active	Wire	Wired LAN+Wireless LAN				
A1(OR)	Blk	E1 active	Wired LAN+Wireless LAN+LTE			Main	GNSS	WL/BT
Pi(RD)	Off	WD Normal						
` ′	On	WD Error	Pin	Signal	Pin	S	ignal	
Di/CD)	Off	LIcor OEE	1 1	GND	9	CAM	1 C P	


On User ON <CSI>[Internal]



ı	PIN	Signal	Pin	Signal
1	1	GND	9	CAM1_C_P
1	2	CAM1_D0_N	10	GND
ı	3	CAM1_D0_P	11	CAM_GPIO
	4	GND	12	NC
	5	CAM1_D1_N	13	I2C1_SCL[GPIO45]
	6	CAM1_D1_P	14	I2C2_SDA[GPI044]
	7	GND	15	3.3V
	8	CAM1_C_N	16-30	NC

<GPIO>[Internal]

RasPi GPIO40pin (same layout as Raspberry Pi 40pin BM40B-SRDS-G-TF)



The GPIOs of CM4 are 3.3V level. The total GPIO load is up to 50mA. For detailed specifications, please refer to the CM4 datasheet

Confirmed Devices [Reference]

This is confirmation with the factory default image.

It depends on customer's software environment.

M.2 SSD TS128GMTE452T, 256,512G model [0-70°C]/Transcend


TS128GMTE452T-I, 256,512G model [-40 to 85°C]/Transcend TS128GMTE452T2, 256,512G model [-20 to 75°C]/Transcend

M.2 WWAN EM7431, EM7430 /Sierra Wireless T2U Nano/TP-LINK company USB Wifi LM808/LM technologies

CSI Camera Raspberry Pi Camera Module 2, Camera Module 2 NoIR Raspberry Pi High Quality Camera

Raspberry Pi Camera Module 3/ Raspberry Pi Foundation





Device List

Signal	Device	Port or connection	Comments
E0:GLAN	CM4	eth0	10/100/1000Mbps
E1:FLAN	LAN9514i	eth1	10/100Mbps
Security IC	ATECC508A	i2c-0/0x60	i2c0: GPIO0,1
(option)			
RTC	DS3231SN	i2c-0/0x68	i2c0: GPIO0,1
OPT:i2c	CM4/GPIO0,1	i2c-0/	i2c0: GPIO0,1
OPT:RS-232	MCP2200-I	ttyACM0	3-wire, max. 250kbps
OPT:RS-485	MCP2200-I	ttyACM0	2-wire, max. 400kbps
CSI:i2c	CM4/GPI44,45	GPIO44,45/i2c-1	i2c1: GPIO44,45 / when not using WD
CSI	CM4/CAM1	CAM1	MIPI CSI-2 2-lanes
WD Enable	MAX6373KA+T	GPIO44/Out	SET0 (SET1: Always High, SET2: Always Low)
WD Reset	MAX6373KA+T	GPIO45/Out	WDI


Note) It may be changed depending on the Raspberry Pi OS side.

Watchdog (WD) timer and CSI connection

SW1: Watchdog or CSI can be switched by selecting GPIO44,45. Watchdog (WD) and CSI cannot be used at the same time. When WD is selected, GPIO44 and 45 are for WD operation. In addition, when SW3: No.1 of protection SW is off, the reset is forcibly disabled. When CSI is selected, GPIO44 and 45 are used as i2c for CSI.


Software

The boot device of this unit is the onboard eMMC of CM4. Booting from an SSD is also possible. The microSD slot is not for system boot. Turn on the eMMC write switch, connect the USB cable, and use the rpiboot program to read and write images. In addition, the USB port is only for eMMC write.



All data given are in line with the actual state of art and therefore not binding. HARTING reserves the right to modify designs without giving the relevant reasons.


Dimensions and installation adapter



Optional accessories

Optional ac	cessories	Part Number		
PWR	M8 A-code	•	1m	21348100489010
cable	4-pin fema	le to open end	2m	21348100489020
E1[FLAN]	M8 A-code	4 pin male	1m	72M8M4RM4010LI
cable		to RJ45 Plug	2m	72M8M4RM4020LI
		to RJ45 Jack	0.2m	72T17001449
OPT	M5 4-pin m	nale to open end	1m	72M5M4010G0
cable			2m	72M5M4020G0
E0[GLAN]	ix plug to	to RJ45 Plug	1m	33480653830010
ix cable	cable			33480653830020
		to RJ45 Jack	0.2m	72T17001450IX
Mount	DIN rail mo	ount adapter		20952000004
kit	wall mount	kit		20953000007
Antenna	LTE mono	pole antenna IP20		72MICA0000254
fot LTE	SMA screv	V		
	LTE flat an	itenna IP67		72MICA0000225
	mounted o	n glass or plastic		
	LTE magn	etic mount antenna I	72MICA0000252	
	mounted n	nagnetically on a me		
	3-in-1 ante	nna IP67	72MICA0000255	
	GPS+2x40	OMIM 6		
	mounted o	n glass or plastic		

Ordering information





Picture




Product Specifications

Processor		Broadcom BCM2711, Quad core @ 1.5GHz				
Memory		RAM4GB, eMMC32GB (Depend on model)				
OS		Raspberry Pi OS				
Interface	Front	1x PWR : Power input, 2-line				
		1x LAN : FLAN 1ch				
		1x OPT*1 : i2c/RS-232/485 selectable				
		1x USB : PushPull USB2.0 Host Type-A				
		[Option]1x WLAN IEEE 802.11 b/g/n/ac, Bluetooth 5.0, BLE				
		[Option]1x LTE(M.2 slot/EM7431)				
	Back	1x USB-C : USB Type-C(eMMC writing only)				
		1x SW : eMMC write switch				
		1x microSD : microSD slot				
	Inter	1x M.2 slot B-key*2, 1x nanoSIM slot				
	nal	1x CSI, 1xGPIO 40p				
LED, Button		P: Power status, A1: LAN status				
		Pi: User custom/WD error				
RTC/NVRAM		BR1225[or CR1225] Backup RTC				
Watchdog		Built-in hardware watchdog				
Power/		BASIC: DC10.7V28.8V/				
Consumpt		12W(incl.USB 500mAx1)				
Temperati	ure	Operating Temp.:-2060°C, Storage:-2585°C				
Humidity		Operating Humi.:0~95%(non-condensing)				
IP grade		IP65				
housing m		Aluminum powder coating				
Dimension	าร	W132 x D89x H35 mm (excluding protrusions)				
Weight		BAISC: Approx.540g				
Vibration/shock		IEC 60068-2-6 / IEC 60068-2-27				
EMI		Radiated emissions EN55016-2-3				
EMS		Electrostatic radiation immunity EN 61000-4-2				
		Radio frequency electromagnetic fields EN 61000-4-3				
		Fast transient burst EN 61000-4-4				
Installation	method	DIN rail mounting, wall mounting(Option)				

- *1 The speed is variable, but Data bit: 8, Parity: N, Stop bit: 1 are fixed.
- *2 This is not a full pin connection. USB2.0, PCIe, and SIM are connected.

Details of each part



Features

- Industrial Raspberry Pi 4 (CM4)
- New processor, up to 2x faster than CM3
- Raspberry Pi OS compatible (Ubuntu requres 4GB or more RAM)
- DC12/24V power input
- Wide operating temperature range and high noise resistance
- M8, M5 connectors with high vibration resistance and connection reliability
- Robust aluminum die-cast housing
- Supports wall mount and DIN rail mount
- On-board eMMC (SD card is not used for boot)
- microSD slot for data storage
- Internal M.2 slot for SSD and WWAN expansion
- Raspi40p connector for expansion board
- Built-in battery backup RTC
- Highly reliable hardware watchdog


Interface

<Connector pin layout>






4pin Male F1 connector [FLAN]



OPT connector



*1 pin for power output is no output by default

M8 A-coded
4pin Female
:LED>

<ANT SMA port> [Option]

LED	Sts.	Comments	Туре	9		ANT2	ANT1	ANT0
P(GR)	Off	No power supply	Wire	d LAN				
' '	On	Power OK	Wire	d LAN+LTE		Main	GNSS	Aux
A0(OR)	Blk	E0 active	Wired LAN+Wireless LAN			WL/BT		
A1(OR)	Blk	E1 active	Wire	d LAN+Wireless LAN	Main	GNSS	WL/BT	
Pi(RD)	Off	WD Normal						
` ′	On	WD Error	Pin	Signal	Pin	S	ignal	
Pi(GR)	Off	User OFF	1	GND	9	CAM	1_C_P	
(,	On	User ON	2	CAM1_D0_N	10	GND		
0301 014			3	CAM1 D0 P	11	CAM	GPIO	

<CSI>[Internal]



		Signal		Signal
1	1	GND	9	CAM1_C_P
1	2	CAM1_D0_N	10	GND
_	3	CAM1_D0_P	11	CAM_GPIO
	4	GND	12	NC
	5	CAM1_D1_N	13	I2C1_SCL[GPIO45]
	6	CAM1_D1_P	14	I2C2_SDA[GPI044]
	7	GND	15	3.3V
	8	CAM1_C_N	16-30	NC

<GPIO>[Internal]

RasPi GPIO40pin (same layout as Raspberry Pi 40pin BM40B-SRDS-G-TF)





The GPIOs of CM4 are 3.3V level.

The total GPIO load is up to 50mA. For detailed specifications, please refer to the CM4 datasheet.

Confirmed Devices [Reference]

This is confirmation with the factory default image

It depends on customer's software environment.

M.2 SSD TS128GMTE452T, 256,512G model [0-70°C]/Transcend

TS128GMTE452T-I, 256,512G model [-40 to 85°C]/Transcend TS128GMTE452T2, 256,512G model [-20 to 75°C]/Transcend


EM7431, EM7430 /Sierra Wireless M.2 WWAN USB Wifi T2U Nano/TP-LINK company

LM808/LM technologies CSI Camera

Raspberry Pi Camera Module 2, Camera Module 2 NoIR Raspberry Pi High Quality Camera Raspberry Pi Camera Module 3/ Raspberry Pi Foundation



Internal datails



Device List

Signal	Device	Port or connection	Comments
E0:GLAN	CM4	eth0	10/100/1000Mbps
E1:FLAN	LAN9514i	eth1	10/100Mbps
Security IC	ATECC508A	i2c-0/0x60	i2c0: GPIO0,1
(option)			
RTC	DS3231SN	i2c-0/0x68	i2c0: GPIO0,1
OPT:i2c	CM4/GPIO0,1	i2c-0/	i2c0: GPIO0,1
OPT:RS-232	MCP2200-I	ttyACM0	3-wire, max. 250kbps
OPT:RS-485	MCP2200-I	ttyACM0	2-wire, max. 400kbps
CSI:i2c	CM4/GPI44,45	GPIO44,45/i2c-1	i2c1: GPIO44,45 / when not using WD
CSI	CM4/CAM1	CAM1	MIPI CSI-2 2-lanes
WD Enable	MAX6373KA+T	GPIO44/Out	SET0 (SET1: Always High, SET2: Always Low)
WD Reset	MAX6373KA+T	GPIO45/Out	WDI


Note) It may be changed depending on the Raspberry Pi OS side.

Watchdog (WD) timer and CSI connection

SW1: Watchdog or CSI can be switched by selecting GPIO44,45. Watchdog (WD) and CSI cannot be used at the same time. When WD is selected, GPIO44 and 45 are for WD operation. In addition, when SW3: No.1 of protection SW is off, the reset is forcibly disabled. When CSI is selected, GPIO44 and 45 are used as i2c for CSI.

Software


The boot device of this unit is the onboard eMMC of CM4. Booting from an SSD is also possible. The microSD slot is not for system boot. Turn on the eMMC write switch, connect the USB cable, and use the rpiboot program to read and write images. In addition, the USB port is only for eMMC write



All data given are in line with the actual state of art and therefore not binding. HARTING reserves the right to modify designs without giving the relevant reasons.


2 I2C

Dimensions and installation adapter



Optional accessories

Optional ac	cessories	Part Number			
PWR	M8 A-code	21348100489010			
cable	4-pin female to open end	2m	21348100489020		
E1[FLAN]	M8 A-code 1m		72M8M4RM4010LI		
cable	4 pin male to RJ45 Plug	2m	72M8M4RM4020LI		
	M8 A-code	0.2m	72T17001449		
	4 pin male to RJ45 Jack				
OPT	M5 4-pin male to open end	1m	72M5M4010G0		
cablle		2m	72M5M4020G0		
PushPull	PushPull USB	1m	09454451911		
cable	to standard USB 2.0	2m	09454451913		
	Type-A	5m	09454451915		
PushPull	PushPull protectioncap	Short	09 45 845 0009		
cover		Long	09 45 845 0015		
	PushPull easy cover	NBR	72PPCAP01		
Dust	for M8 Male(PWR)/IP67		72MICA0000033		
сар	for M8 Femal (E1)/IP67		72MICA0000034		
	for M5 Female(OPT)/IP67	72MICA0000035			
Mount	DIN rail mount adapter		20952000004		
kit	wall mount kit		20953000007		
Antenna	LTE monopole antenna IP20		72MICA0000254		
LTE	SMA screw				
	LTE flat antenna IP67		72MICA0000225		
	mounted on glass or plastic				
	LTE magnetic mount antenna I	72MICA0000252			
	mounted magnetically on a me	tal surface			
	3-in-1 antenna IP67		72MICA0000255		
	GPS+2x4G MIMO				
	mounted on glass or plastic				



Ordering information

When selecting CodeSys, please use 32bit OS. If you select 64bit, the license 32bit OS. IT you select oron,
key will not be the Raspberry Pi version

and you will not be able to use it.

4 32/SSD128GB 0 None 5 32/SSD256GB 1 RS-232C[standard] 6 32/SSD512GB 4.5.6: NVMe fast SSD 3 RS-485

> 0 None[standard] 1 CodeSys

0 None[standard] Reserved

RAM size [GB]

MICA-R4 BASIC RJ Plus IP20



Picture




Product Specifications

		-			
Processor		Broadcom BCM2711, Quad core @ 1.5GHz			
Memory		RAM4GB, eMMC32GB (Depend on model)			
OS		Raspberry Pi OS			
Interface	Front	1x PWR :Power input, 2-line			
		2x LAN :FLAN[100Mbs]x1ch, GLAN[1000Mbs] x1ch			
		1x OPT*1 :i2c/RS-232/485 selectable			
		1x USB :USB2.0 Host Type-A			
		1x IO :Di 2ch(Photocoupler input,DC5V-24V)			
		Do 2ch(Photorelay output,DC48V,			
		Max 400mA:25°C/Max250mA:60°C)			
		Ai 4ch(Non-isolated, resolution 12bit, Max3.3kSPS)			
		0-5V/0-10V(100V)			
		1x Maintenance :Maintenance port(reserved)			
		[Option]1x WLAN IEEE 802.11 b/g/n/ac, Bluetooth 5.0, BLE			
		[Option]1x LTE(M.2 slot/EM7431)			
	Back	1x USB-C : USB Type-C(eMMC writing only)			
		1x SW : eMMC write switch			
		1x microSD : microSD slot			
	Inter	1x M.2 slot B-key*2, 1x nanoSIM slot			
	nal 1x CSI, 1xGPIO 40p				
LED, Button		P: Power status, A0,1: LAN status			
		Pi: User custom/WD error			
RTC/NVR		BR1225[or CR1225] Backup RTC			
Watchdog	l	Built-in hardware watchdog			
Power/		DC10.7V~28.8V			
Consumpt		12.5W(incl.USB 500mAx1)			
Temperat	ure	Operating Temp.: -2060°C, Storage:-2585°C			
Humidity		Operating Humi.:095%(non-condensing)			
IP grade		IP20			
		Aluminum powder coating			
Dimensions		W132 x D87 x H35 mm (excluding protrusions)			
Weight		Approx. 570g			
Vibration/s	shock	IEC 60068-2-6 / IEC 60068-2-27			
EMI		Radiated emissions EN55016-2-3			
EMS		Electrostatic radiation immunity EN 61000-4-2			
		Radio frequency electromagnetic fields EN 61000-4-3			
	Fast transient burst EN 61000-4-4				
Installation method DIN rail mounting, wall mounting(Option)					


- *1 The speed is variable, but Data bit: 8, Parity: N, Stop bit: 1 are fixed.
- *2 This is not a full pin connection. USB2.0, PCIe, and SIM are connected.

Details of each part




Features

- Industrial Raspberry Pi 4 (CM4)
- New processor, up to 2x faster than CM3
- Raspberry Pi OS compatible (Ubuntu requres 4GB or more RAM)
- DC12/24V power input
- Wide operating temperature range and high noise resistance
- M8, M5, ix connectors with high vibration resistance and connection reliability
- Robust aluminum die-cast housing
- Supports wall mount and DIN rail mount
- On-board eMMC (SD card is not used for boot)
- microSD slot for data storage
- Internal M.2 slot for SSD and WWAN expansion
- Raspi40p connector for expansion board
- Built-in battery backup RTC
- Highly reliable hardware watchdog




<led:< th=""><th>></th><th></th><th colspan="4"><ant port="" sma=""> [Option]</ant></th></led:<>	>		<ant port="" sma=""> [Option]</ant>			
LED	Sts.	Comments	Туре	ANT2	ANT1	ANT0
P(GR)	Off	No power supply	Wired LAN			
	On	Power OK	Wired LAN+LTE	Main	GNSS	Aux
A1(OR)	Blk	E1 active	Wired LAN+Wireless LAN	WL/BT		
Pi(RD)	Off	WD Normal	Wired LAN+Wireless LAN+LTE	Main	GNSS	WL/BT
	On	WD Error				
Pi(GR)	Off	User OFF				
	On	User ON				



<GPIO>[Internal] RasPi GPIO40pin

(same layout as Raspberry Pi 40pin BM40B-SRDS-G-TF)




The GPIOs of CM4 are 3.3V level. The total GPIO load is up to 50mA. For detailed specifications, please check the CM4 datasheet

System Reserved [IO connection]

MICA-R4 BASIC RJ Plus IP20





Device List

BR1225 or CR1225 Battery

SW5:COM select ON:RS-485 OFF:RS-232 SW4:COM select ON:RS-485 OFF:RS-232


Signal	Device	Port or connection	Comments
E0:GLAN(reserved)	CM4	eth0_	10/100/ <u>1</u> 000Mbps
E1:FLAN	LAN9514i	eth1_	10/100Mbps
Security IC (option)	ATECC508A	i2c-0/0x60	i2c0:GPIO0,1
RTC	DS3231SN	i2c-0/0x68	i2c0:GPIO0,1
OPT:i2c	CM4/GPIO0,1	i2c-0/	i2c0:GPIO0,1
OPT:RS-232	MCP2200-I	ttyACM1	3-wire, max. 250kbps
OPT:RS-485	MCP2200-I	ttyACM1	2-wire, max. 400kbps
CSI:i2c	CM4/GPI44,45	GPIQ44,45/i2c-1	i2c1: GPIO44,45 / when not using WD
CSI	CM4/CAM1	CAM1	MIPI CSI-2 2-lanes
Pi LED(green)	CM4	GPIO6/Out	2 color LED : Pi LED(green) and WDerror LED(red)
WD Enable	MAX6373KA+T	GPIO44/Out	SET0 (SET1: Always High, SET2: Always Low)
WD Reset	MAX6373KA+T	GPIO45/Out	WD
Di0,1	CM4	GPIO16,17/In	Photocoupler input DC5V ~ 24V, +/- common compatible
Do0,1	CM4	GPIO18,19/Out	Photorelay output
			MaxDC48V, 250mA,+/-common compatible
Ai0,1,2,3	ADS1015	i2c-1/0x48	Resolution 12bit, 4ch input, 0-5V/0-2000cnt
			FSR = ±2.048 V, single-ended inputs
		Note) It	may be changed depending on the Raspberry Pi OS side.

Note) It may be changed depending on the Raspberry Pi OS sid


A13

Software

The boot device of this unit is the onboard eMMC of CM4. Booting from an SSD is also possible. The microSD slot is not for system boot. Turn on the eMMC write switch, connect the USB cable, and use the rpiboot program to read and write images. In addition, the USB port is only for eMMC write.




Dimensions and installation adapter




Optional accessories

Optional acc	cessories	Part Number		
PWR	M8 A-code 1m		21348100489010	
cable	4-pin female to open end	2m	21348100489020	
OPT	M5 4-pin male to open end	1m	72M5M4010G0	
cable		2m	72M5M4020G0	
E0[GLAN]	ix plug to to RJ45 Plug	1m	33480653830010	
ix cable		2m	33480653830020	
	to RJ45 Jack	0.2m	72T17001450IX	
Mount	DIN rail mount adapter		20952000004	
kit	wall mount kit		20953000007	
Antenna	LTE monopole antenna IP20	LTE monopole antenna IP20		
fot LTE	SMA screw			
	LTE flat antenna IP67		72MICA0000225	
	mounted on glass or plastic			
	LTE magnetic mount antenna	IP65	72MICA0000252	
	mounted magnetically on a mounted			
	3-in-1 antenna IP67	72MICA0000255		
	GPS+2x4G MIMO			
	mounted on glass or plastic			

IO connection[example]



Ordering information



MICA-R4 BASIC Plus IP65






Product Specifications

Drocosso	Processor Broadcom BCM2711, Quad core @ 1.5GHz			
Memory		RAM4GB, eMMC32GB (Depend on model)		
OS		Raspberry Pi OS		
	Front	1x PWR :Power input, 2-line		
Intoridoo		1x LAN :FLAN[100Mbs]x1ch		
		1x OPT*1 :i2c/RS-232/485 selectable		
		1x USB :USB2.0 Host Type-A		
		4x IO :M5 IO port [Dix2ch,Dox2ch,Aix4ch]		
		Ai: 0-5V/0-10(100)V[default]		
		1x Maintenance :Maintenance port(reserved)		
		[Option]1x WLAN IEEE 802.11 b/g/n/ac, Bluetooth 5.0, BLE		
		[Option]1x LTE(M.2 slot/EM7431)		
	Back	1x USB-C : USB Type-C(eMMC writing only)		
		1x SW : eMMC write switch		
		1x microSD : microSD slot		
	Inter	1x M.2 slot B-key*2, 1x nanoSIM slot		
	nal	1x CSI, 1xGPIO 40p		
LED, Button		P: Power status, A0,1: LAN status		
		Pi: User custom/WD error		
RTC/NVR		BR1225[or CR1225] Backup RTC		
Watchdog		Built-in hardware watchdog		
Power/		DC10.7V~28.8V		
Consumpt		12.5W(incl.USB 500mAx1)		
Temperat	ure	Operating Temp.: -2060°C, Storage:-2585°C		
Humidity		Operating Humi.:095%(non-condensing)		
IP grade		IP65		
		Aluminum powder coating		
Dimensions		W132 x D89 x H35 mm (excluding protrusions)		
Weight Vibration/shock		Approx. 540g		
	shock	IEC 60068-2-6 / IEC 60068-2-27		
EMI		Radiated emissions EN55016-2-3		
EMS		Electrostatic radiation immunity EN 61000-4-2		
		Radio frequency electromagnetic fields EN 61000-4-3		
I	411	Fast transient burst EN 61000-4-4		
Installation method DIN rail mounting, wall mounting(Option)				


- *1 The speed is variable, but Data bit: 8, Parity: N, Stop bit: 1 are fixed.
- *2 This is not a full pin connection. USB2.0, PCIe, and SIM are connected.

Details of each part




Features

- Industrial Raspberry Pi 4 (CM4)
- New processor, up to 2x faster than CM3
- Raspberry Pi OS compatible (Ubuntu requres 4GB or more RAM)
- DC12/24V power input
- Wide operating temperature range and high noise resistance
- M8, M5 connectors with high vibration resistance and connection reliability
- Robust aluminum die-cast housing
- Supports wall mount and DIN rail mount
- On-board eMMC (SD card is not used for boot)
- microSD slot for data storage
- Internal M.2 slot for SSD and WWAN expansion
- Raspi40p connector for expansion board
- Built-in battery backup RTC
- Highly reliable hardware watchdog



Type ANT Pin Signa CAM1_C_P Wired LAN 2 CAM1_D0_N 3 CAM1_D0_P Wired LAN+LTE GND CAM_GPIO Main 10 Wired LAN+ WL/BT NC I2C1_SCL[GPI045] I2C2_SDA[GPI044] Wireles LAN GND CAM1_D1_N CAM1_D1_P Wired LAN+ Wireless LAN+LTE settings GND 15 3.3V CAM1 16-30 NC <GPIO>[Internal]




RasPi GPIO 40pin (same layout as Raspberry Pi 40pin BM40B-SRDS-G-TF)

System Reserved [SD connection]
System Reserved [IO connection]

The GPIOs of CM4 are 3.3V level.
The total GPIO load is up to 50mA.
For detailed specifications, please check the CM4 datasheet.


IO connection example




Analog input - and V1, V2 power supply 0V are connected internally. Connector shield and power supply 0V* are connected internally. Please limit the power output to a maximum of 200mA per channel and the total power supply to 0.8A. The digital output is a photorelay output with a maximum of 250mA @ 60°C.

MICA-R4 BASIC Plus IP65







USB2.0


Device List

Signal	Device	Port or connection	10/ ©ัฒน์ที่ตับอัฟปร ps
E0:GLAN(reserved)	CM4	eth0	10/100Mbps
E1:FLAN	LAN9514i	eth1	12c0:GPIO0,1
Security IC(option)	ATECC508A	i2c-0/0x60	12c0:GPIO0,1
RTC	DS3231SN	i2c-0/0x68	i2c0:GPIO0,1
OPT:i2c	CM4/GPIO0,1	i2c-0/	3-wire, max. 250kbps
OPT:RS-232	MCP2200-I	ttyACM1	2-wire, max. 400kbps
OPT:RS-485	MCP2200-I	ttyACM1	i2c1: GPIO44,45 / when not using WD
CSI:i2c	CM4/GPI44,45	GPIO44,45/i2c-1	MIPI CSI-2 2-lanes
CSI	CM4/CAM1	CAM1	SET0 (SET1: Always High, SET2: Always Low)
WD Enable	MAX6373KA+T	GPIO44/Out	WD
WD Reset	MAX6373KA+T	GPIO45/Out	Photocoupler input DC5V ~ 24V, +/- common compatible
Di0,1	CM4	GPIO16,17	Photorelay output
Do0,1	CM4	GPIO18,19	MaxDC48V, 250mA,+/-common compatible Resolution 12bit, 4ch input, 0-5V/0-2000cnt
Ai0,1,2,3	ADS1015	i2c-3/0x48	FSR = 12.048 V, single-ended inputs


Note) It may be changed depending on the Raspberry Pi OS side

Software

The boot device of this unit is the onboard eMMC of CM4. Booting from an SSD is also possible. The microSD slot is not for system boot. Turn on the eMMC write switch, connecting the control of the cont the USB cable, and use the rpiboot program to read and write images. In addition, the USB port is only for eMMC write




Dimensions and installation adapter



Optional accessories

Optional ac	cessories	Part Number	
PWR	M8 A-code	1m	21348100489010
cable	4-pin female to open end	21348100489020	
E1[FLAN]	M8 A-code	1m	72M8M4RM4010LI
cable	4 pin male to RJ45 Plug	2m	72M8M4RM4020LI
	M8 A-code	0.2m	72T17001449
	4 pin male to RJ45 Jack		
OPT	M5 4-pin male to open end	1m	72M5M4010G0
cablle		2m	72M5M4020G0
PushPull	PushPull USB	1m	09454451911
cable	to standard USB 2.0	2m	09454451913
	Type-A	5m	09454451915
PushPull	PushPull protectioncap	Short	09 45 845 0009
cover		Long	09 45 845 0015
	PushPull easy cover	NBR	72PPCAP01
Dust	for M8 Male(PWR)/IP67		72MICA0000033
сар	for M8 Femal (E1)/IP67		72MICA0000034
	for M5 Female(OPT)/IP67		72MICA0000035
Mount	DIN rail mount adapter		20952000004
kit	wall mount kit		20953000007
Antenna LTE	LTE monopole antenna IP20 SMA screw		72MICA0000254
	LTE flat antenna IP67		72MICA0000225
	mounted on glass or plastic		
	LTE magnetic mount antenna	72MICA0000252	
	mounted magnetically on a me	tal surface	
	3-in-1 antenna IP67		72MICA0000255
	GPS+2x4G MIMO		
	mounted on glass or plastic		

Ordering information



All data given are in line with the actual state of art and therefore not binding. HARTING reserves the right to modify designs without giving the relevant reasons L LTE



Picture




Product Specifications

Processor		Broadcom BCM2711, Quad core @ 1.5GHz		
Memory		RAM4GB, eMMC32GB (Depend on model)		
OS		Raspberry Pi OS		
Interface	Front	1x PWR : Power input, 2-line		
		2x LAN : FLAN 1ch, GLAN 1ch		
		1x OPT*1 : i2c/RS-232/485 selectable		
		3x USB : USB2.0 Host Type-A		
		1x Maintenance :Maintenance port(reserved)		
		[Option]1x WLAN IEEE 802.11 b/g/n/ac, Bluetooth 5.0, BLE		
		[Option]1x LTE(M.2 slot/EM7431)		
	Back	1x USB-C : USB Type-C(eMMC writing only)		
		1x SW : eMMC write switch		
		1x microSD : microSD slot		
	Inter	1x M.2 slot B-key*2, 1x nanoSIM slot		
	nal	1x CSI, 1xGPIO 40p		
LED, Butto	on	P: Power status, A0,1: LAN status		
		Pi: User custom/WD error		
RTC/NVR	AM	BR1225[or CR1225] Backup RTC		
Watchdog		Built-in hardware watchdog		
Power/		USB:DC10.7V28.8V/		
Consumpt	ion	17.5W(incl.USB 500mAx3)		
Temperatu	ıre	Operating Temp.: -2060°C, Storage:-2585°C		
Humidity		Operating Humi.:095%(non-condensing)		
IP grade		IP20		
housing material				
Dimensions		W132 x D87.1 x H35 mm (excluding protrusions)		
Weight		USB:Approx.560g		
Vibration/shock		IEC 60068-2-6 / IEC 60068-2-27		
EMI		Radiated emissions EN55016-2-3		
EMS		Electrostatic radiation immunity EN 61000-4-2		
		Radio frequency electromagnetic fields EN 61000-4-3		
		Fast transient burst EN 61000-4-4		
Installation method DIN rail mounting, wall mounting(Opt		DIN rail mounting, wall mounting(Option)		

- *1 The speed is variable, but Data bit: 8, Parity: N, Stop bit: 1 are fixed.
- *2 This is not a full pin connection. USB2.0, PCIe, and SIM are connected.

Details of each part



Features

- Industrial Raspberry Pi 4 (CM4)
- New processor, up to 2x faster than CM3
- Raspberry Pi OS compatible (Ubuntu requres 4GB or more RAM)
- DC12/24V power input
- Wide operating temperature range and high noise resistance
- M8, M5, ix connectors with high vibration resistance and connection reliability
- Robust aluminum die-cast housing
- Supports wall mount and DIN rail mount
- On-board eMMC (SD card is not used for boot)
- microSD slot for data storage
- M.2 slot inside SSD and WWAN expansion
- Raspi40p connector for expansion board
- Built-in battery backup RTC
- Highly reliable hardware watchdog

Interface

<Connector pin layout>



E0 connector
ix type-A jack

F1 connector [FLAN]

M8 A-coded 4pin Female

OPT connector



Pin	Col.	i2c	RS232	RS485
1	BR	3.3V/5V/none*		
2	WH	SCL	TXD	Α
		0V(RS232:SG)		
4	BK	SDA	RXD	В

*1 pin for power output is no output by default.

10 N.C 1 BR TX+
2 WH RX+
3 BL RX-

10/100M TX+

TX-

N.C

N.C N.C RX+

N.C

8 N.C BI_DA+

BI_DA-

BI DB+

GND

BI DD+


GND

<LED> <ANT SMA port> [Option]

LED	Sts.	Comments	Туре	9		ANT2	ANT1	ANT0
P(GR)	Off	No power supply	Wired LAN					
	On	Power OK	Wire	d LAN+LTE		Main	GNSS	Aux
A0(OR)	Blk	E0 active	Wire	d LAN+Wireless LAN	I \	NL/BT		
A1(OR)	Blk	E1 active	Wire	d LAN+Wireless LAN	I+LTE I	Main	GNSS	WL/BT
Pi(RD)	Off	WD Normal						
	On	WD Error	Pin	Signal	Pin		Signal	
Pi(GR)	Off	User OFF	1	GND	9	CAM	1_C_P	
` ′	On	User ON	2	CAM1_D0_N	10	GND		
			3	CAM1_D0_P	11	CAM	_GPIO	
<csi>[</csi>	Inter	mal]	4	GND	12	NC	NC	
	FPC connector			CAM1_D1_N	13 I2C1 SCL[GPI045]		O45]	
			6	CAM1_D1_P	14 I2C2 SDA[GPI044]		IO44]	
			7 GND 15 3.3V					
No. 1/			8	CAM1_C_N	16-3) NC		

<GPIO>[Internal]

RasPi GPIO40pin (same layout as Raspberry Pi 40pin BM40B-SRDS-G-TF)



The GPIOs of CM4 are 3.3V level. The total GPIO load is up to 50mA. For detailed specifications, please check the CM4 datasheet

Confirmed Devices [Reference]

This is confirmation with the factory default image It depends on customer's software environment.

M.2 SSD TS128GMTE452T, 256,512G model [0-70°C]/Transcend TS128GMTE452T-I, 256,512G model [-40 to 85°C]/Transcend


TS128GMTE452T2, 256,512G model [-20 to 75°C]/Transcend

EM7431, EM7430 /Sierra Wireless M.2 WWAN USB Wifi T2U Nano/TP-LINK company LM808/LM technologies Wifi

Raspberry Pi Camera Module 2, Camera Module 2 NoIR Raspberry Pi High Quality Camera CSI Camera

Raspberry Pi Camera Module 3/ Raspberry Pi Foundation





Device List

Signal	Device	Port or connection	Comments
E0:GLAN	CM4	eth0	10/100/1000Mbps
E1:FLAN	LAN9514i	eth1	10/100Mbps
Security IC	ATECC508A	i2c-0/0x60	i2c0: GPIO0,1
(option)			
RTC	DS3231SN	i2c-0/0x68	i2c0: GPIO0,1
OPT:i2c	CM4/GPIO0,1	i2c-0/	i2c0: GPIO0,1
OPT:RS-232	MCP2200-I	ttyACM0	3-wire, max. 250kbps
OPT:RS-485	MCP2200-I	ttyACM0	2-wire, max. 400kbps
CSI:i2c	CM4/GPI44,45	GPIO44,45/i2c-1	i2c1: GPIO44,45 / when not using WD
CSI	CM4/CAM1	CAM1	MIPI CSI-2 2-lanes
WD Enable	MAX6373KA+T	GPIO44/Out	SET0 (SET1: Always High, SET2: Always Low)
WD Reset	MAX6373KA+T	GPIO45/Out	WDI

Note) It may be changed depending on the Raspberry Pi OS side


switch

- Win32 DiskImager(read/write image)


Watchdog (WD) timer and CSI connection SW1: Watchdog or CSI can be switched by selecting GPIO44,45. Watchdog (WD) and CSI cannot be used at the same time. When WD is selected, GPIO44 and 45 are for WD operation. In addition, when SW3: No.1 of protection SW is off, the reset is forcibly disabled. When CSI is selected, GPIO44 and 45 are used as i2c for CSI.

Software

The CM4's onboard eMMC will be the boot device for this unit. Booting from an SSD is also possible. microSD slot is not for system boot. Turn on the eMMC write switch, connect the USB cable, and use the rpiboot program to read and write images. In addition, this The USB port is an eMMC write-only port.




Dimensions and installation adapter



Optional accessories

Optional ac	cessories			Part Number
PWR	M8 A-code		1m	21348100489010
cable	4-pin female to open end		2m	21348100489020
E1[FLAN]	M8 A-code	4 pin male	1m	72M8M4RM4010LI
cable		to RJ45 Plug	2m	72M8M4RM4020LI
		to RJ45 Jack	0.2m	72T17001449
OPT	M5 4-pin n	nale to open end	1m	72M5M4010G0
cable			2m	72M5M4020G0
E0[GLAN]	ix plug to	to RJ45 Plug	1m	33480653830010
ix cable			2m	33480653830020
		to RJ45 Jack	0.2m	72T17001450IX
Mount	DIN rail mo	ount adapter		20952000004
kit	wall mount	t kit		20953000007
Antenna	LTE mono	pole antenna IP20		72MICA0000254
fot LTE	SMA screv	V		
	LTE flat ar	itenna IP67		72MICA0000225
	mounted o	n glass or plastic		
	LTE magn	etic mount antenna	72MICA0000252	
	mounted n	nagnetically on a me	tal surface	
	3-in-1 ante	enna IP67		72MICA0000255
	GPS+2x40	G MIMO		
	mounted o	n glass or plastic		

Ordering information



All data given are in line with the actual state of art and therefore not binding. HARTING reserves the right to modify designs without giving the relevant reasons. L LTE



Picture




Product Specifications

Processor		Broadcom BCM2711, Quad core @ 1.5GHz				
Memory		RAM4GB, eMMC32GB (Depend on model)				
OS		Raspberry Pi OS				
Interface	Front	1x PWR : Power input, 2-line				
IIILEIIACE		1x LAN				
				table		
		3x USB	1x OPT*1 : i2c/RS-232/485 selectable 3x USB : PushPull USB2.0 Host Type-A			
	Back		: USB Type-C(eMMC v			
	Dack	1x SW	* ' '	9 5,)		
		1x microSE) : microSD slot			
	Inter	1x M.2 slot	B-key*2, 1x nanoSIM slo	ot		
	nal	1x CSI, 1x0	GPIO 40p			
LED, Butte	on	P: Power status, A1: LAN status				
		Pi: User custom/WD error				
RTC/NVR	AM	BR1225[or CR1225] Backup RTC				
Watchdog		Built-in hardware watchdog				
Power/		USB: DC10.7V28.8V/17.5W(incl. USB 500mAx3)				
Consump						
Temperat	ure	Operating Temp.:-2060°C, Storage:-2585°C				
Humidity		Operating Humi::0~95%(non-condensing)				
IP grade		IP65				
housing m		Aluminum powder coating				
Dimension	าร	W132 x D89x H35 mm (excluding protrusions)				
Weight		USB: Approx.570g				
Vibration/s	shock	IEC 60068-2-6 / IEC 60068-2-27				
EMI		Radiated e		EN55016-2-3		
EMS			c radiation immunity	EN 61000-4-2		
			uency electromagnetic fie			
		Fast transient burst EN 61000-4-4				
Installation method		DIN rail mounting, wall mounting(Option)				

- *1 The speed is variable, but Data bit: 8, Parity: N, Stop bit: 1 are fixed.
- *2 This is not a full pin connection. USB2.0, PCIe, and SIM are connected.

Details of each part



Features

- Industrial Raspberry Pi 4
- New processor, up to 2x faster than CM3
- Raspberry Pi OS compatible(Ubuntu require RAM4G or more)
- DC12/24V power input
- Wide operating temperature range and high noise resistance
- M8, M5 connectors with high vibration resistance and connection reliability
- Robust aluminum die-cast housing
- Supports wall mount and DIN rail mount
- On-board eMMC (SD card is not used for boot)
- microSD slot for data storage
- M.2 slot inside SSD expansion
- Raspi40p connector for expansion board
- Built-in battery backup RTC
- Highly reliable hardware watchdog

Interface

<Connector pin layout>



F1 connector



1 2 M5

4 0 3 4pin Female						
Pin	Col.	i2c	RS232	RS485		
1	BR	3.3V/5V/none*				
2	WH	SCL	TXD	Α		
3	BL 0V(RS232:SG)					
4 BK SDA RXD B						
t nin	for no	wor outp	ut io no out	out by defeu		

OPT connector

TEL A NII			
[FLAN]	Pin	Col.	Signal
	1	BR	TX+
	2	WH	RX+
M8 A-coded	3	BL	RX-
4pin Female	4	BK	TX-

<LED>


LED	Sts.	Comments			
P(GR)	Off	No power supply			
	On	Power OK			
A0(OR)		E0 active			
A1(OR)	Blk	E1 active			
Pi(RD)	Off	WD Normal			
' '	On	WD Error			
Pi(GR)	Off	User OFF			
	On	User ON			
-001 11 4 11					

<csi>[Internal]</csi>
FPC connecto

FPC connector	
	_
	ŧ.
No. 1	

П		Olgilai	1 111	Olgital
1	1	GND	9	CAM1_C_P
1	2	CAM1_D0_N	10	GND
J	3	CAM1_D0_P	11	CAM_GPIO
	4	GND	12	NC
	5	CAM1_D1_N		I2C1_SCL[GPI045]
	6	CAM1_D1_P	14	I2C2_SDA[GPI044]
	7	GND	15	3.3V
	8	CAM1_C_N	16-30	NC

<GPIO>[Internal]





The total GPIO load is up to 50mA. For detailed specifications, please check the CM4 datasheet.

Confirmed Devices [Reference]

This is confirmation with the factory default image It depends on customer's software environment.

M.2 SSD

TS128GMTE452T, 256,512G model [0-70°C]/Transcend TS128GMTE452T-I, 256,512G model [-40 to 85°C]/Transcend TS128GMTE452T2, 256,512G model [-20 to 75°C]/Transcend


EM7431, EM7430 /Sierra Wireless M.2 WWAN T2U Nano/TP-LINK company LM808/LM technologies USB Wifi

Wifi CSI Camera

Raspberry Pi Camera Module 2, Camera Module 2 NoIR Raspberry Pi High Quality Camera

Raspberry Pi Camera Module 3/ Raspberry Pi Foundation





Device List

Signal	Device	Port or connection	Comments			
E0:GLAN	CM4	eth0	10/100/1000Mbps			
E1:FLAN	LAN9514i	eth1	10/100Mbps			
Security IC	ATECC508A	i2c-0/0x60	i2c0: GPIO0,1			
(option)						
RTC	DS3231SN	i2c-0/0x68	i2c0: GPIO0,1			
OPT:i2c	CM4/GPIO0,1	i2c-0/	i2c0: GPIO0,1			
OPT:RS-232	MCP2200-I	ttyACM0	3-wire, max. 250kbps			
OPT:RS-485	MCP2200-I	ttyACM0	2-wire, max. 400kbps			
CSI:i2c	CM4/GPI44,45	GPIO44,45/i2c-1	i2c1: GPIO44,45 / when not using WD			
CSI	CM4/CAM1	CAM1	MIPI CSI-2 2-lanes			
WD Enable	MAX6373KA+T	GPIO44/Out	SET0 (SET1: Always High, SET2: Always Low)			
WD Reset	MAX6373KA+T	GPIO45/Out	WDI			

Note) It may be changed depending on the Raspberry Pi OS side


Watchdog (WD) timer and CSI connection

- Win32 DiskImager(read/write image)


SW1: Watchdog or CSI can be switched by selecting GPIO44,45. Watchdog (WD) and CSI cannot be used at the same time. When WD is selected, GPIO44 and 45 are for WD operation. In addition, when SW3: No.1 of protection SW is off, the reset is forcibly disabled. When CSI is selected, GPIO44 and 45 are used as I2c for CSI.

Software

The CM4's onboard eMMC will be the boot device for this unit. Booting from an SSD is also possible. microSD slot is not for system boot. Turn on the eMMC write switch, connect the USB cable, and use the rpiboot program to read and write images. In addition, this




Dimensions and installation adapter



Optional accessories

Optional ac	cessories	Part Number	
PWR	M8 A-code	1m	21348100489010
cable	able 4-pin female to open end		21348100489020
E1[FLAN]	M8 A-code	1m	72M8M4RM4010LI
cable	4 pin male to RJ45 Plug	2m	72M8M4RM4020LI
	M8 A-code	0.2m	72T17001449
	4 pin male to RJ45 Jack		
OPT	M5 4-pin male to open end	1m	72M5M4010G0
cablle		2m	72M5M4020G0
PushPull	PushPull USB	1m	09454451911
cable	to standard USB 2.0	2m	09454451913
	Type-A	5m	09454451915
PushPull	PushPull protectioncap	Short	09 45 845 0009
cover		Long	09 45 845 0015
	PushPull easy cover	NBR	72PPCAP01
Dust	for M8 Male(PWR)/IP67	72MICA0000033	
сар	for M8 Femal (E1)/IP67	72MICA0000034	
	for M5 Female(OPT)/IP67	72MICA0000035	
Mount	DIN rail mount adapter		20952000004
kit	wall mount kit		20953000007
Antenna	LTE monopole antenna IP20		72MICA0000254
LTE	SMA screw		
	LTE flat antenna IP67		72MICA0000225
	mounted on glass or plastic		
	LTE magnetic mount antenna I	72MICA0000252	
	mounted magnetically on a me	tal surface	
	3-in-1 antenna IP67	72MICA0000255	
	GPS+2x4G MIMO		
	mounted on glass or plastic		

Ordering information



All data given are in line with the actual state of art and therefore not binding. HARTING reserves the right to modify designs without giving the relevant reasons.

LTE[not select]

MICA-R4 GPIO IP20



Picture




Product Specifications

Processo	r	Drandom DCM2711 Quad care @ 1 FCUT			
		Broadcom BCM2711, Quad core @ 1.5GHz			
Memory		RAM4GB, eMMC32GB (Depend on model)			
OS		Raspberry Pi OS			
Interface	Front	1x PWR : Power input, 2-line 2x LAN : FLAN 1ch, GLAN 1ch			
		1x OPT*1 : i2c/RS-232/485 selectable			
		1x USB : USB2.0 Host Type-A 1x GPIO : D-SUB15p GPIO12ch, GND,3.3V,5V			
		[Option]1x WLAN IEEE 802.11 b/g/n/ac			
		Bluetooth 5.0, BLE			
		[Option]1x LTE(M.2 slot/EM7431)			
	Back	1x USB-C : USB Type-C(eMMC writing only) 1x SW : eMMC write switch			
		1x Svv : eMMC write switch			
	Internal				
	internai	1x M.2 slot B-key*2, 1x nanoSIM slot			
LED D.A	4	1x CSI, 1xGPIO 40p P: Power status. A0.1: LAN status			
LED, But	ton	Pi: User custom/WD error			
DTC/NIV/	2414	BR1225[or CR1225] Backup RTC			
RTC/NVF		Built-in hardware watchdog			
Watchdo	9	GPIO:DC10.7V28.8V/			
Consump	ation	12W(incl. USB 500mAx1)			
Tempera					
Humidity	lure	Operating Temp.: -20~60°C, Storage:-25~85°C			
IP grade		Operating Humi.:0~95%(non-condensing)			
	natorial	IP20			
housing material Dimensions		Aluminum powder coating			
Weight		W132 x D87 x H35 mm (excluding protrusions)			
Vibration/shock		GPIO:Approx.550g IEC 60068-2-6 / IEC 60068-2-27			
EMI					
EMS		Radiated emissions EN55016-2-3			
EIVIO		Electrostatic radiation immunity EN 61000-4-2			
		Radio frequency electromagnetic fields EN 61000-4-3			
Inetallatio	n mothad	Fast transient burst EN 61000-4-4			
installation method		DIN rail mounting, wall mounting(Option)			

- *1 The speed is variable, but Data bit: 8, Parity: N, Stop bit: 1 are fixed.
- *2 This is not a full pin connection. USB2.0, PCIe, and SIM are connected.

Details of each part



Features

- Industrial Raspberry Pi 4 (CM4)
- New processor, up to 2x faster than CM3
- Raspberry Pi OS compatible (Ubuntu regures 4GB or more RAM)
- DC12/24V power input
- Wide operating temperature range and high noise resistance
- M8, M5, ix connectors with high vibration resistance and connection reliability
- Robust aluminum die-cast housing
- Supports wall mount and DIN rail mount
- On-board eMMC does not use SD memory for boot
- microSD slot for data storage
- Internal M.2 slot for SSD and WWAN expansion
- Raspi40p connector for expansion board


3 BL 0V(V1) 4 BK 0V(V2)

10/100M TX+

BI_DA+

- Built-in battery backup RTC
- Highly reliable hardware watchdog

Interface





	F
E0 connector	
[GLAN]	
[02,]	



4pin Female




TX

OPT connector 2 M5

4 6 3 4pin Female					
Pin	Col.	i2c	RS232	RS485	
1	BR	3.3V/5	V/none*1		
2	WH	SCL	TXD	Α	
3	BL	0V(RS	232:SG)		
4	BK	SDA	RXD	В	

*1 pin for power output is no output by default.



Pin	Oigilai	Pin	Signal	
Pin	GPIO	Pin	GPIO	
1	GND	9	GPIO9	
2	GPIO2	10	GPIO10	
3	GPIO3	11	GPIO11	
4	GPIO4	12	GPIO12	
5	GPIO5	13	GPIO13	
6	GPIO6	14	3.3V out	
7	GPI07	15	5V out	
8	GPIO8			

<led></led>					
LED	Sts.	Comments			
P(GR)	Off	No power supply			
	On	Power OK			
A0(OR)		E0 active			
A1(OR)	Blk	E1 active			
Pi(RD)	Off	WD Normal			
	On	WD Error			
Pi(GR)	Off	User OFF			

AI(UK)	DIK	E i active				
Pi(RD)	Off	WD Normal				
	On	WD Error				
Pi(GR)	Off	User OFF				
	On	User ON				
<csi>[Internal]</csi>						
FPC connector						

	<an i="" port="" swa=""> [Optior</an>	ij		
;	Type	ANT2	ANT1	ANT0
у	Wired LAN			
	Wired LAN+LTE		Main	GNSS
	Wired LAN+Wireless LAN		WL/BT	
	Wired LAN+Wireless LAN+LTE		Main	WL/BT
		_		

н				
1	Pin	Signal	Pin	Signal
1	1	GND	9	CAM1_C_P
1	2	CAM1_D0_N	10	GND
ı	3	CAM1_D0_P	11	CAM_GPIO
	4	GND	12	NC
	5	CAM1_D1_N	13	I2C1_SCL[GPIO45]
	6	CAM1_D1_P	14	I2C2_SDA[GPI044]
	7	GND	15	3.3V
	8	CAM1_C_N	16-30	NC

<GPIO>[Internal] RasPi GPIO40pin (


ne lavout as Raspberry Pi 40pin BM40B-SRDS-G-TF)

Nasri GriO40piii	(Sallie le	your as ix	aspucity	FT 40PIII DIVI	40D-311D3-G-11)
D-sub15p-14	3.3V	100 2	5V	D-sub15p-15	
D-sub15p-2	GPIO2	3 0 0 4	5V		
D-sub15p-3	GPIO3	500 6	Ground	D-sub15p-1	
D-sub15p-4	GPIO4	7008	GPIO14		
•	Ground	9 0 0 10	GPIO15		
	GPIO17	11 🔾 🔾 12	GPIO18		
	GPIO27	13 0 0 14	Ground		
	GPIO22	15 0 0 16	GPIO23		
	3.3V	17 0 0 18	GPI024		
D-sub15p-10	GPIO10	19 0 0 20	Ground		
D-sub15p-9	GPIO9	21 0 0 22	GPI025		
D-sub15p-11	GPIO11	23 🔵 🔾 24	GPIO8	D-sub15p-8	
•	Ground	25 0 0 26	GPIO7	D-sub15p-7	
	ID_SD	27 🔵 🔘 28	ID_SC		
D-sub15p-5	GPIO5	29 🔵 🔘 30	Ground		
D-sub15p-6	GPIO6	31 🔵 🔘 32	GPIO12	D-sub15p-12	
D-sub15p-13	GPIO13	33 0 0 34	Ground		
	GPIO19	35 🔵 🔘 36	GPIO16		: System Reserved
	GPIO26	37 🔵 🔘 38	GPIO20		(GPIO connector)
	Ground	39 0 0 40	GPIO21		: System Reserved
					(SD connection)
The GPIOs of	CM4 are	3.3V level	The total	al GPIO load	is up to 50mA

For detailed specifications, please refer to the CM4 datasheet.

MICA-R4 GPIO IP20





Device List

Signal	Device	Port or connection	Comments
E0:GLAN	CM4	eth0	10/100/1000Mbps
E1:FLAN	LAN9514i	eth1	10/100Mbps
Security IC (option)	ATECC508A	i2c-0/0x60	i2c0: GPIO0,1
RTC	DS3231SN	i2c-0/0x68	i2c0: GPIO0,1
OPT:i2c	CM4/GPIO0,1	i2c-0/	i2c0: GPIO0,1
OPT:RS-232	MCP2200-I	ttyACM0	3-wire, max. 250kbps
OPT:RS-485	MCP2200-I	ttyACM0	2-wire, max. 400kbps
CSI:i2c	CM4/GPI44,45	GPIO44,45/i2c-1	i2c1: GPIO44,45 / when not using WD
CSI	CM4/CAM1	CAM1	MIPI CSI-2 2-lanes
WD Enable	MAX6373KA+T	GPIO44/Out	SET0 (SET1: Always High, SET2: Always Low)
WD Reset	MAX6373KA+T	GPIO45/Out	WDI


Note) It may be changed depending on the Raspberry Pi OS side

Watchdog (WD) timer and CSI connection


SW1: Watchdog or CSI can be switched by selecting GPIO44,45. Watchdog (WD) and CSI cannot be used at the same time. When WD is selected, GPIO44 and 45 are for WD operation. In addition, when SW3: No.1 of protection SW is off, the reset is forcibly disabled. When CSI is selected, GPIO44 and 45 are used as i2c for CSI.

Software

The boot device of this unit is the onboard eMMC of CM4. Booting from an SSD is also possible. The microSD slot is not for system boot. Turn on the eMMC write switch, conne the USB cable, and use the rpiboot program to read and write images. In addition, the USB port is only for eMMC write



Dimensions and installation adapter



Optional accessories

Optional ac	Optional accessories Part Number					
PWR	M8 A-code	•	1m	21348100489010		
cable	4-pin fema	le to open end	2m	21348100489020		
E1[FLAN]	M8 A-code	4 pin male	1m	72M8M4RM4010LI		
cable		to RJ45 Plug	2m	72M8M4RM4020LI		
		to RJ45 Jack	0.2m	72T17001449		
OPT	M5 4-pin n	nale to open end	1m	72M5M4010G0		
cable			2m	72M5M4020G0		
E0[GLAN]	ix plug to	to RJ45 Plug	1m	33480653830010		
ix cable			2m	33480653830020		
		to RJ45 Jack	0.2m	72T17001450IX		
Mount	DIN rail me	ount adapter		20952000004		
kit	wall moun	t kit		20953000007		
Antenna	LTE mono	pole antenna IP20		72MICA0000254		
fot LTE	SMA screv	V				
	LTE flat ar	ntenna IP67	72MICA0000225			
	mounted o	n glass or plastic				
	LTE magn	etic mount antenna	72MICA0000252			
	mounted n	nagnetically on a me				
	3-in-1 ante	enna IP67		72MICA0000255		
	GPS+2x40					
	mounted o	n glass or plastic				

Confirmed Devices [Reference]

This is confirmation with the factory default image


It depends on customer's software environment. M.2 SSD TS128GMTE452T, 256,512G model [0-70°C]/Transcend

TS128GMTE452T-I, 256,512G model [-40 to 85°C]/Transcend TS128GMTE452T2, 256,512G model [-20 to 75°C]/Transcend

M 2 WWAN EM7431, EM7430 /Sierra Wireless USB Wifi T2U Nano/TP-LINK company Wifi

LM808/LM technologies CSI Camera Raspberry Pi Camera Module 2. Camera Module 2 NoIR

Raspberry Pi High Quality Camera
Raspberry Pi Camera Module 3/ Raspberry Pi Foundation



MICA-R4 USB GPIO IP20



Picture




Product Specifications

		•			
Processor		Broadcom BCM2711, Quad core @ 1.5GHz			
Memory		RAM4GB, eMMC32GB (Depend on model)			
os		Raspberry Pi OS			
Interface	Front	1x PWR :Power input, 2-line			
		2x LAN : FLAN 1ch, GLAN 1ch			
		1x OPT*1 : i2c/RS-232/485 selectable			
		2 x USB : USB2.0 Host Type-A			
		1x GPIO : D-SUB15p GPIO12ch, GND,3.3V,5V			
		[Option]1x WLAN IEEE 802.11 b/g/n/ac			
		Bluetooth 5.0, BLE			
		[Option]1x LTE(M.2 slot/EM7431)			
	Back	1x USB-C : USB Type-C(eMMC writing only)			
		1x SW : eMMC write switch			
		1x microSD : microSD slot			
	Internal	1x M.2 slot B-key*2, 1anox microSIM slot			
		1x CSI, 1xGPIO 40p			
LED, Butt	on	P: Power status, A0,1: LAN status			
		Pi: User custom/WD error			
RTC/NVR		BR1225[or CR1225] Backup RTC			
Watchdoo	3	Built-in hardware watchdog			
Power/		USB/GPIO:DC10.7V28.8V/			
Consump		15W(incl. USB 500mAx2)			
Temperat	ure	Operating Temp.: -20~60°C, Storage:-25~85°C			
Humidity		Operating Humi.:0~95%(non-condensing)			
IP grade		IP20			
housing material		Aluminum powder coating			
Dimensions		W132 x D87 x H35 mm (excluding protrusions)			
Weight		USB/GPIO: Approx.570g			
Vibration/shock		IEC 60068-2-6 / IEC 60068-2-27			
EMI		Radiated emissions EN55016-2-3			
EMS		Electrostatic radiation immunity EN 61000-4-2			
		Radio frequency electromagnetic fields EN 61000-4-3			
		Fast transient burst EN 61000-4-4			
Installation method		DIN rail mounting, wall mounting(Option)			

- *1 The speed is variable, but Data bit: 8, Parity: N, Stop bit: 1 are fixed.
- *2 This is not a full pin connection. USB2.0, PCIe, and SIM are connected.


Details of each part



Features

- Industrial Raspberry Pi 4 (CM4)
- New processor, up to 2x faster than CM3
- Raspberry Pi OS compatible (Ubuntu require RAM4G or more)
- DC12/24V power input
- Wide operating temperature range and high noise resistance
- M8, M5, ix connectors with high vibration resistance and connection reliability
- Robust aluminum die-cast housing
- Supports wall mount and DIN rail mount
- On-board eMMC (SD card is not used for boot)
- microSD slot for data storage
- M.2 slot inside SSD and WWAN expansion
- Raspi40p connector for expansion board
- Built-in battery backup RTC
- Highly reliable hardware watchdog

Interface



<led></led>			<ant port="" sma=""> [Option]</ant>								
LED	Sts.	Comments	Туре)		Α	NT2	AN			
P(GR)	Off	No power supply	Wire	Wired LAN							
	On	Power OK	Wired LAN+LTE								
A0(OR)	Blk	E0 active	Wired LAN+Wireless LAN -					WL/B			
A1(OR)	Blk	E1 active	Wired	LAN+Wireless LAN	I+LTE			Main			
Pi(RD)	Off	WD Normal									
. ,	On	WD Error	Pin	Signal	Pin		S	ignal			
Pi(GR)	Off	User OFF	1	GND	9		CAM	1_C_F			
(,				04444 00 41	10		0110				

	On	User ON									
<csi>[Internal]</csi>											
FPC connector											

٦	Pin	Signal	Pin	Signal
1	1	GND	9	CAM1_C_P
1	2	CAM1_D0_N	10	GND
_	3	CAM1_D0_P	11	CAM_GPIO
	4	GND	12	NC
	5	CAM1_D1_N	13	I2C1_SCL[GPI045]
	6	CAM1_D1_P	14	I2C2_SDA[GPI044]
	7	GND	15	3.3V
	8	CAM1_C_N	16-30	NC

GNSS ---WL/BT

<GPIO>[Internal]


RasPi GPIO40pin (same layout as Raspberry Pi 40pin BM40B-SRDS-G-TF)

ĸа	SPI GPIO40pin	(same ia	ayout as	Ka	spberry	PI 40pin Bivi	40B-5RD	IS-G-TF)
	D-sub15p-14	3.3V	100	2	5V	D-sub15p-15		
	D-sub15p-2	GPIO2	300	4	5V			
	D-sub15p-3	GPIO3	500	6	Ground	D-sub15p-1		
	D-sub15p-4	GPIO4	700	8	GPIO14			
		Ground	900	10	GPIO15			
		GPIO17	11 0 0	12	GPIO18			
		GPIO27	13 🔾 🔾	14	Ground			
		GPIO22	15 0 0	16	GPIO23			
		3.3V	17 0 0	18	GPIO24			
	D-sub15p-10	GPIO10	19 0 0	20	Ground			
	D-sub15p-9	GPIO9	21 0 0	22	GPIO25			
	D-sub15p-11	GPIO11	23 0 0	24	GPIO8	D-sub15p-8		
		Ground	25 0 0	26	GPIO7	D-sub15p-7		
		ID_SD	27 0 0	28	ID SC			
	D-sub15p-5	GPIO5	29 0 0	30	Ground			
	D-sub15p-6	GPIO6	31 0 0	32	GPIO12	D-sub15p-12		
	D-sub15p-13	GPIO13		34				
		GPIO19	35 0 0	36	GPIO16		:	System Reserved
		GPIO26	37 0 0	38	GPIO20			(GPIO connector
		Ground		40	GPIO21			System Reserved
								(SD connection)
	The GPIOs of 0	CM4 are	3.3V lev	el.	The tota	I GPIO load	is up to 5	i0mA.

The GPIOs of CM4 are 3.3V level.The total GPIO load is up to 50mA For detailed specifications, please check the CM4 datasheet.

MICA-R4 USB GPIO IP20





Device List

Signal	Device	Port or connection	Comments
E0:GLAN	CM4	eth0	10/100/1000Mbps
E1:FLAN	LAN9514i	eth1	10/100Mbps
Security IC (option)	ATECC508A	i2c-0/0x60	i2c0: GPIO0,1
RTC	DS3231SN	i2c-0/0x68	i2c0: GPIO0,1
OPT:i2c	CM4/GPIO0,1	i2c-0/	i2c0: GPIO0,1
OPT:RS-232	MCP2200-I	ttyACM0	3-wire, max. 250kbps
OPT:RS-485	MCP2200-I	ttyACM0	2-wire, max. 400kbps
CSI:i2c	CM4/GPI44,45	GPIO44,45/i2c-1	i2c1: GPIO44,45 / when not using WD
CSI	CM4/CAM1	CAM1	MIPI CSI-2 2-lanes
WD Enable	MAX6373KA+T	GPIO44/Out	SET0 (SET1: Always High, SET2: Always Low)
WD Reset	MAX6373KA+T	GPIO45/Out	WDI


Note) It may be changed depending on the Raspberry Pi OS side

Watchdog (WD) timer and CSI connection


SW1: Watchdog or CSI can be switched by selecting GPIO44,45. Watchdog (WD) and CSI cannot be used at the same time. When WD is selected, GPIO44 and 45 are for WD operation. In addition, when SW3: No.1 of protection SW is off, the reset is forcibly disabled. When CSI is selected, GPIO44 and 45 are used as i2c for CSI

Software

The CM4's onboard eMMC will be the boot device for this unit. Booting from an SSD is also possible. microSD slot is not for system boot. Turn on the eMMC write switch, connect the USB cable, and use the rpiboot program to read and write images. In addition, this The USB port is an eMMC write-only port



Dimensions and installation adapter



Optional accessories

Optional ac	cessories		Part Number	
PWR	M8 A-code	;	1m	21348100489010
cable	4-pin fema	le to open end	2m	21348100489020
E1[FLAN]	M8 A-code	4 pin male	1m	72M8M4RM4010LI
cable		to RJ45 Plug	2m	72M8M4RM4020LI
		to RJ45 Jack	0.2m	72T17001449
OPT	M5 4-pin n	nale to open end	1m	72M5M4010G0
cable			2m	72M5M4020G0
E0[GLAN]	ix plug to	to RJ45 Plug	1m	33480653830010
ix cable	' -		2m	33480653830020
		to RJ45 Jack	0.2m	72T17001450IX
Mount	DIN rail mo	ount adapter		20952000004
kit	wall mount	kit		20953000007
Antenna	LTE mono	pole antenna IP20	72MICA0000254	
fot LTE	SMA screv	V		
	LTE flat an	itenna IP67	72MICA0000225	
	mounted o	n glass or plastic		
	LTE magn	etic mount antenna	P65	72MICA0000252
	mounted n	nagnetically on a me		
	3-in-1 ante	nna IP67		72MICA0000255
	GPS+2x40	S MIMO		
	mounted o	n glass or plastic		

Confirmed Devices [Reference]

This is confirmation with the factory default image.

It depends on customer's software environment.


M.2 SSD TS128GMTE452T, 256,512G model [0-70°C]/Transcend

TS128GMTE452T-I, 256,512G model [-40 to 85°C]/Transcend TS128GMTE452T2, 256,512G model [-20 to 75°C]/Transcend

M.2 WWAN EM7431, EM7430 /Sierra Wireless USB Wifi T2U Nano/TP-LINK company

LM808/LM technologies CSI Camera

Raspberry Pi Camera Module 2, Camera Module 2 NoIR Raspberry Pi High Quality Camera Raspberry Pi Camera Module 3/ Raspberry Pi Foundation



All data given are in line with the actual state of art and therefore not binding. HARTING reserves the right to modify designs without giving the relevant reasons LTE

MICA-R4 DIO IP20



Picture




Product Specifications

Processor		Broadcom BCM2711, Quad core @ 1.5GHz						
Memory		, ,						
OS		RAM4GB, eMMC32GB (Depend on model)						
Interface	I	Raspberry Pi OS 1x PWR : Power input, 2-line						
іптепасе	Front	1 /						
		2x LAN : FLAN 1ch, GLAN 1ch						
		1x OPT*1 : i2c/RS-232/485 selectable						
		1x USB : USB2.0 Host Type-A						
		1x CN1 : Di16ch[14ch] (PNP)/2.4mA at 24VDC						
		Do8ch(PNP)/Pushpull0.1A,High-side0.5A						
		COM 1ch RS-232/RS485(2w)						
		CAN 1 or 2ch/CAN 2.0B,CAN FD 1Mbps						
		[Option]1x WLAN IEEE 802.11 b/g/n/ac,Bluetooth5.0,BLE						
		[Option]1x LTE(M.2 slot/EM7431)						
	Back	1x USB-C : USB Type-C(eMMC writing only)						
		1x SW : eMMC write switch						
		1x microSD : microSD slot						
	Internal	1x M.2 slot B-key*2, 1x nanoSIM slot						
		1x CSI, 1xGPIO 40p						
LED, Button		P: Power status, A0,1: LAN status, Di/Do,						
		Pi: User custom/WD error, Di/Do: CN1-Di/Do status						
RTC/NVRAI	M	BR1225[or CR1225] Backup RTC,						
		MCP79410-I:CR1632 backup RTC, NVRAM						
Watchdog		Built-in hardware watchdog						
Power/Cons		,						
Temperature	9	Operating Temp.: -2060°C, Storage:-2585°C						
Humidity		Operating Humi.:095%(non-condensing)						
IP grade		IP20						
housing mat	erial	Aluminum powder coating						
Dimensions		W132 x D87 x H35 mm (excluding protrusions)						
Weight		DIO: Approx.570g						
Vibration/shock		IEC 60068-2-6 / IEC 60068-2-27						
EMI		Radiated emissions EN55016-2-3						
EMS		Electrostatic radiation immunity EN 61000-4-2						
		Radio frequency electromagnetic fields EN 61000-4-3						
		Fast transient burst EN 61000-4-4						
Installation r	nethod	DIN rail mounting, wall mounting(Option)						

*1 The speed is variable, but Data bit: 8, Parity: N, Stop bit: 1 are fixed. *2 This is not a full pin connection. USB2.0, PCle, and SIM are connected

Details of each part



Features

- Industrial Raspberry Pi 4 (CM4)
- New processor, up to 2x faster than CM3
 Raspberry Pi OS compatible (Ubuntu requres 4GB or more RAM)
- DC12/24V power input
- Wide operating temperature range and high noise resistance M8, M5, ix connectors with high vibration resistance and

connection reliability

- Robust aluminum die-cast housing
- Supports wall mount and DIN rail mount
- On-board eMMC does not use SD memory for boot
- microSD slot for data storage
- Internal M.2 slot for SSD and WWAN expansion
- Raspi40p connector for expansion board
- Built-in battery backup RTC
- Highly reliable hardware watchdog

Interface



M8 A-coded 4pin Male

E0 connector [GLAN] ix type-A

<CN1 port>

Div	Sig	nal			
Pin	10/100M	1G			
1	TX+	BI_DA+			
2	TX-	BI_DA-			
3	N.C.	GND			
4	N.C.	BI_DC+			
5	N.C.	BI_DC-			
6	RX+	BI_DB+			
7	RX-	BI_DB-			
8	N.C.	GND			
9	N.C.	BI_DD+			
10	N.C.	BI_DD-			

1 pin for power output is no output by default E1 connector [FLAN] M8 A-coded 4pin Female

1 BR TX+ 2 WH RX+ BL RX-BK TX-4

OPT connector

3 4pin Female

1 BR 3.3V/5V/none* 2 WH SCL TXD 3 BL 0V(RS232:SG)

3 BL 0V(RS232:SG) 4 BK SDA RXD

Connection side Harness side
- Housing 32-pin: PHDR-32VS
- Contact: BPHD/SPHD-001T-P0.5 AWG26...22/Outer diameter Φ1.0...1.5mm Contact: BPHD/SPHD-002T-P0.5 AWG28...24/ Outer diameter Φ 0.9...1.5mm

i2c RS232 RS485

Pin	1	3	5	7	9	11	13	15*	17	19	21	23	25	27	29	31
Sig	Di	Di	Di	Di	Di	Di	Di	Di14		Do	Do	Do	Do	RS232(Tx)		CAN
nal	0	2	4	6	8	10	12	Or CAN	Do	0	2	4	6	/RS485(+)	485 SG	0+
	Digital Input(PNP) 1+ GND Digital Output(PNP)															
Pin	2	4	6	8	10	12	14	16*	18	20	22	24	26	28	30	32
Sig	Di	Di	Di	Di	Di	Di	Di	Di14	Di	Do	Do	Do	Do	RS232(Rx)	Di	CAN
nal	1	3	5	7	9	11	13	or	Do	1	3	5	7	/RS485(-)	COM	0-
								CAN		ı		ıtput(F			DC24V	

*:This signal changes depending on the can1/2 port selection.

The rating per digital output point is 0.1A in the default setting. Make sure that the total current value does not exceed 1A. For protection, an automatic reset fuse is built into the device.



:System Used (extension board CN10) :System Used (extension board CN6) System Used


The GPIOs of CM4 are 3.3V level. The total GPIO load is up to 50mA. For detailed specifications, please refer to the CM4 datasheet

<led></led>			<ant port="" sma=""> [Option</ant>]		
LED	Sts.	Comments	Type	ANT2	ANT1	ANT0

LED	Sts.	Comments	Type)		ANIZ	ANTI	ANTU		
P(GR)	Off	No power supply	Wire	d LAN						
	On	Power OK	Wire	d LAN+LTE				Main		
A0(OR)	Blink	E0 active	Wire	d LAN+Wireless LAN	1			WL/BT		
A1(OR)	Blink	E1 active	Wire	d LAN+Wireless LAN	1+LTE			None		
Pi(RD)	Off	WD Normal	<cs< td=""><td>I>[Internal] E</td><td>PC con</td><td>nector</td><td></td><td></td></cs<>	I>[Internal] E	PC con	nector				
	On	WD Error		. [4				
Pi(GR)	Off	User OFF		No.1						
	On	User ON								
Di0.1	Off	Di OFF	Pin	Signal	Pin		Signal			
	ON	Di ON	1	GND	9	CAM	1_C_P			
Do0.1	Off	Do OFF	2	CAM1_D0_N	10	GND				
- /	On	Do ON	3	CAM1_D0_P	11		_GPIO			
			4	GND	12	NC				
			5	CAM1_D1_N	13	I2C1	SCL[GP	IO45]		
			6	CAM1_D1_P	14	I2C2	SDA[GP	1044]		
			7	GND	15	3.3V				
			8	CAM1 C N	16-3	0 NC				


MICA-R4 DIO IP20





Internal DIP switch setting

The board on the left side of MCIA-R4 is the IO board. Only the lower board is mounted on the DIO model. Analog range and serial communication can be selected by switching the switch



Device List


Main board	Main board side device									
Signal	Device	Port or connection	Comments							
E0:GLAN	CM4	eth0	10/100/1000Mbps							
E1:FLAN	LAN9514i	eth1	10/100Mbps							
Security IC	ATECC508A	i2c-0/0x60*	i2c0: GPIO0,1							
(option)										
RTC	DS3231SN	i2c-0/0x68	i2c0: GPIO0,1							
OPT:i2c	CM4/GPIO0,1	i2c-0/	i2c0: GPIO0,1							
OPT:RS-232	MCP2200-I	ttyACM0	3-wire, max. 250kbps							
OPT:RS-485	MCP2200-I	ttyACM0	2-wire, max. 400kbps							
CSI:i2c	CM4/GPI44,45	GPIO44,45/i2c-1	i2c1: GPIO44,45 / when not using WD							
CSI	CM4/CAM1	CAM1	MIPI CSI-2 2-lanes							
WD Enable	MAX6373KA+T	GPIO44/Out	SET0 (SET1: Always High, SET2: Always Low)							
WD Reset	MAX6373KA+T	GPIO45/Out	WDI							

* Not recognized at i2c bus speed of 400kHz or higher. Therefore, it does not conflict with MCP4728.

IO expansion board side device						
Signal	Device	Port or connection	Comments			
Di0Di15	MCP23S17	spidev1.0/0	Lower board			
Do0Do7	MCP23S17	spidev1.0/1	Lower board[1.1/0 JP selectable]			
Spare		spidev1.1	Lower board			
CAN0	MCP2518FD	spidev0.0:can0	Lower board			
CAN1	MCP2518FD	spidev0.1:can1	Lower board			
RTC,NVRAM*1	CP74910	i2c-5/0x57,6F	Lower board			
RS-232/485	TXD1,RXD1	ttyAMA0	Lower board RS232 3w Max.250kbps			
			RS485 2w Max.500kbps			


*1 When using MCP79410 on the Raspberry Pi OS side, NVRAM cannot be connected on the Codesys side.

Dimensions and installation adapter



Optional accessories

Optional ac	cessories	Part Number		
PWR	M8 A-code 1m			21348100489010
cable	4-pin fema	le to open end	2m	21348100489020
E1[FLAN]	M8 A-code	4 pin male	1m	72M8M4RM4010LI
cable		to RJ45 Plug	2m	72M8M4RM4020LI
		to RJ45 Jack	0.2m	72T17001449
OPT	M5 4-pin n	nale to open end	1m	72M5M4010G0
cable			2m	72M5M4020G0
E0[GLAN]	ix plug to	to RJ45 Plug	1m	33480653830010
ix cable			2m	33480653830020
		to RJ45 Jack	0.2m	72T17001450IX
Mount	DIN rail mo	ount adapter		20952000004
kit	wall mount	kit		20953000007
Antenna	LTE mono	pole antenna IP20		72MICA0000254
fot LTE	SMA screv	V		
	LTE flat ar	tenna IP67		72MICA0000225
	mounted o	n glass or plastic		
	LTE magn	etic mount antenna I	72MICA0000252	
	mounted n	nagnetically on a me		
	3-in-1 ante	nna IP67	72MICA0000255	
	GPS+2x40	OMIM 6		
	mounted o	n glass or plastic		



1 CodeSys

LTE

All data given are in line with the actual state of art and therefore not binding. HARTING reserves the right to modify designs without giving the relevant reasons.

and you will not be able to use it.

MICA-R4 Multi IO IP20



Picture




Product Specifications

Processor	-							
Name								
Interface								
Front 2x LAN		1						
2x LAN	Interface	Front						
1x USB : USB2.0 Host Type-A 1x CN1 : Di16ch[14ch] (PNP)/2.4mA at 24VDC Do8ch(PNP)/Pushpull0.1A,High-side0.5A COM 1ch RS-232/RS485(2w) CAN 1 or 2ch/CAN 2.0B,CAN FD 1Mbps 1x CN2 : Di4ch (NPN)/7.2 mA at 24VDC Do4ch (PNP)/High-side0.5A,pushpull0.1A Ai 4ch 16bit(0-5/0-10VDC) Note)ch3 only 0-5/0-100VDC Ao2ch 12bit(0-5/0-10VDC) SPI 1ch/ Max.12Mbps 1x PRG : STM32 programming port 1x Maintenance :Maintenance port(reserved) (Option]1x WLAN IEEE 802.11 b/g/n/ac,Bluetooth5.0,BLE [Option]1x LTE(M.2 slot/EM7431) Back 1x USB-C : USB Type-C(eMMC writing only) 1x SW : eMMC write switch Internal 1x microSD : microSD slot 1x M.2 slot B-key*², 1x nanoSIM slot 1x CSI, 1xGPIO 40p P: Power status, A0,1: LAN status Pi: User custom/WD error, Di/Do: CN1-Di/Do status, USR: User custom, PRG: STM32 Debugger interface, RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I:CR1632 backup RTC, NVRAM Suith-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:095%(non-condensing) IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)		i ioni						
1x CN1								
Do8ch(PNP)/Pushpull0.1A,High-side0.5A								
COM 1ch RS-232/RS485(2w) CAN 1 or 2ch/CAN 2.0B,CAN FD 1Mbps								
CAN 1 or 2ch/CAN 2.0B,CAN FD 1Mbps								
1x CN2								
Do4ch (PNP)/High-side0.5A,pushpull0.1A								
Ai 4ch 16bit(0-5/0-10VDC) Note)ch3 only 0-5/0-10VDC Note)ch3 only 0-5/0-10VDC Ao2ch 12bit(0-5/0-10VDC) SPI 1ch/ Max.12Mbps 1x PRG STM32 programming port 1x Maintenance :Maintenance port(reserved) [Option]1x WLAN IEEE 802.11 b/g/n/ac,Bluetooth5.0,BLE [Option]1x LTE(M.2 slot/EM7431) Back 1x USB-C : USB Type-C(eMMC writing only) 1x SW :eMMC write switch 1x microSD : microSD slot 1x M.2 slot B-key*2 ,1x nanoSIM slot 1x CSI, 1xGPIO 40p LED, Button P: Power status, A0,1: LAN status Pi: User custom/WD error, Di/Do: CN1-Di/Do status, USR: User custom/WD error, Di/Do: CN1-Di/Do status, USR: User custom, PRG: STM32 Debugger interface, RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I:CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:095%(non-condensing) IP grade IP20 I								
Note)ch3 only 0-5/0-100VDC								
Ao2ch 12bit(0-5/0-10VDC) SPI 1ch/ Max.12Mbps								
SPI 1ch/ Max.12Mbps 1x PRG : STM32 programming port 1x Maintenance :Maintenance port(reserved) [Option]1x WLAN IEEE 802.11 b/g/n/ac,Bluetooth5.0,BLE [Option]1x WLAN IEEE 802.11 b/g/n/ac,Bluetooth5.0,BLE [Option]1x LTE(M.2 slot/EM7431) Back			Note)ch3 only 0-5/0-100VDC					
1x PRG : STM32 programming port 1x Maintenance :Maintenance port(reserved) [Option]1x WLAN IEEE 802.11 b/g/n/ac,Bluetooth5.0,BLE [Option]1x LTE(M.2 slot/EM7431) Back 1x USB-C : USB Type-C(eMMC writing only) 1x SW : eMMC write switch Internal 1x microSD : microSD slot 1x M.2 slot B-key*², 1x nanoSIM slot 1x CSI, 1xGPIO 40p LED, Button P: Power status, A0,1: LAN status Pi: User custom/WD error, Di/Do: CN1-Di/Do status, USR: User custom, PRG: STM32 Debugger interface, RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I:CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)								
1x Maintenance :Maintenance port(reserved) [Option]1x WLAN IEEE 802.11 b/g/n/ac,Bluetooth5.0,BLE [Option]1x LTE(M.2 slot/EM7431) Back 1x USB-C : USB Type-C(eMMC writing only) 1x SW : eMMC write switch Internal 1x microSD : microSD slot 1x M.2 slot B-key*², 1x nanoSIM slot 1x CSI, 1xGPIO 40p LED, Button P: Power status, A0,1: LAN status Pi: User custom/WD error, Di/Do: CN1-Di/Do status, USR: User custom, PRG: STM32 Debugger interface, RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I: CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)			SPI 1ch/ Max.12Mbps					
[Option]1x WLAN IEEE 802.11 b/g/n/ac,Bluetooth5.0,BLE [Option]1x LTE(M.2 slot/EM7431)			1x PRG : STM32 programming port					
Internal Internal								
Back 1x USB-C : USB Type-C(eMMC writing only) 1x SW : eMMC write switch 1x microSD : microSD slot 1x microSD : microSD slot 1x M.2 slot B-key*², 1x nanoSIM slot 1x CSI, 1xGPIO 40p 1x CSI, 1xGPIO 50p 1x			[Option]1x WLAN IEEE 802.11 b/g/n/ac,Bluetooth5.0,BLE					
1x SW : eMMC write switch 1x microSD : microSD slot 1x M.2 slot B-key*², 1x nanoSIM slot 1x CSI, 1xGPIO 40p 1x CSI, 1xGPIO 40p P: Power status, A0,1: LAN status Pi: User custom/WD error, Di/Do: CN1-Di/Do status, USR: User custom, PRG: STM32 Debugger interface, RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I:CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.TV28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:095%(non-condensing) IP grade IP20 IP20 IP20 IP20 IP30 IP30 IP30 IP30 IV32 x D87 x H35 mm (excluding protrusions)								
1x SW : eMMC write switch 1x microSD : microSD slot 1x M.2 slot B-key*², 1x nanoSIM slot 1x CSI, 1xGPIO 40p 1x CSI, 1xGPIO 40p P: Power status, A0,1: LAN status Pi: User custom/WD error, Di/Do: CN1-Di/Do status, USR: User custom, PRG: STM32 Debugger interface, RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I:CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.TV28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:095%(non-condensing) IP grade IP20 IP20 IP20 IP20 IP30 IP30 IP30 IP30 IV32 x D87 x H35 mm (excluding protrusions)		Back	1x USB-C : USB Type-C(eMMC writing only)					
Internal 1x M.2 slot B-key*², 1x nanoSIM slot 1x CSI, 1xGPIO 40p P: Power status, A0,1: LAN status Pi: User custom/WD error, Di/Do: CN1-Di/Do status, USR: User custom, PRG: STM32 Debugger interface, RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I: CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)			1x SW : eMMC write switch					
1x M.2 slot B-key*², 1x nanoSIM slot 1x CSI, 1xGPIO 40p P: Power status, A0,1: LAN status Pi: User custom/WD error, Di/Do: CN1-Di/Do status, USR: User custom, PRG: STM32 Debugger interface, RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I: CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)		Internal						
P: Power status, A0,1: LAN status Pi: User custom/WD error, Di/Do: CN1-Di/Do status, USR: User custom, PRG: STM32 Debugger interface, RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I:CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi.:095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)			1x M.2 slot B-key*2, 1x nanoSIM slot					
Pi: User custom/WD error, Di/Do: CN1-Di/Do status, USR: User custom, PRG: STM32 Debugger interface, RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-1:CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp::-2060°C, Storage:-2585°C Humidity Operating Humi::095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)								
USR: User custom, PRG: STM32 Debugger interface, RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I: CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi::095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)	LED, Button							
RST: Reset switch for STM32 RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I:CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)								
RTC BR1225[or CR1225] Backup RTC NVRAM MCP79410-I:CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi.:095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)								
NVRAM MCP79410-I:CR1632 backup RTC, NVRAM Watchdog Built-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:.095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)								
Watchdog Built-in hardware watchdog Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:.095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)								
Power/Consumption DC10.7V28.8V/13.5W(incl. USB 500mAx1) Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi:095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)	NVRAM							
Temperature Operating Temp.: -2060°C, Storage:-2585°C Humidity Operating Humi.:095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)								
Humidity Operating Humi::095%(non-condensing) IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)	Power/Cons							
IP grade IP20 housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)								
housing material Aluminum powder coating Dimensions W132 x D87 x H35 mm (excluding protrusions)								
Dimensions W132 x D87 x H35 mm (excluding protrusions)	g							
	Weight		Multi IO: Approx.610g					
Vibration/shock IEC 60068-2-6 / IEC 60068-2-27		ock						
EMI Radiated emissions EN55016-2-3								
EMS Electrostatic radiation immunity EN 61000-4-2	EMS		Electrostatic radiation immunity EN 61000-4-2					
Radio frequency electromagnetic fields EN 61000-4-3								
			Fast transient burst EN 61000-4-4					
Installation method DIN rail mounting, wall mounting(Option)								

1 The speed is variable, but Data bit: 8, Parity: N, Stop bit: 1 are fixed. *2 This is not a full pin connection. USB2.0, PCIe, and SIM are connected.

Details of each part




Features

- Industrial Raspberry Pi 4(CM4)
- New processor, up to 2x faster than CM3
 Raspberry Pi OS compatible (Ubuntu requres 4GB or more RAM)
- DC12/24V power input
- Wide operating temperature range and high noise resistance
- M8, M5, ix connectors with high vibration resistance and connection reliability
- Robust aluminum die-cast housing
- Supports wall mount and DIN rail mount
- On-board eMMC (SD card is not used for boot)
- microSD slot for data storage
- M.2 slot inside SSD and WWAN expansion
- Raspi40p connector for expansion board
- Built-in battery backup RTC
 Highly reliable hardware watchdog

Interface

-

ix type-A



	Signal					
Pin	10/100M	1G				
1	TX+	BI_DA+				
2	TX-	BI_DA-				
3	N.C.	GND				
4	N.C.	BI_DC+				
5	N.C.	BI_DC-				
6	RX+	BI_DB+				
7	RX-	BI_DB-				
8	N.C.	GND				
9	N.C.	BI_DD+				
10	N.C.	BI_DD-				



OPT connector

3

1 BR 3.3V/5V/none


BR TX+ WH RX+ BL RX-4 BK

Connection side Harness side

- Housing 32-pin: PHDR-32VS - Contact: BPHD/SPHD-001T-P0.5 CN1 <CN1 port> [JST/PHD 32pin co

- Contact: BPHD/SPHD-0011-P0.5 - Contact: BPHD/SPHD-002T-P0.5 AWG28...24/ Outer diameter Φ 0.9...1.5mr RS232(Tx) RS232/ CAN

В



The rating per digital output point is 0.1A in the default setting. Make sure that the total current value does not exceed 1A. For protection, an automatic reset fuse is built into the device. Connection side Harness side

	I2 port				CN2	Pin1 A	- Contac AWG26 - Contac	g 20-pin: PHDR t: BPHD/SPHD 622/Outer dia t: BPHD/SPHD 824/Outer dia	-001T-P meter Φ -002T-P	1.01.5m 0.5
Pin	1	3	5	7	9	11	13	15	17	19
Sig nal		STM Di2 gital Input PN)	STM Di,Do GND	Ai0 Analo	Ai2 g input		STM Do2 tal Output NP)	Ao0 Analog Output	CS1 s	MISO PI
Pin	2	4	6	8	10	12	14	16	18	20
Sig nal		STM Di3 gital Input PN)	Ai,Ao GND	Ai1 Analo	Ai3 g input	STM Do1 STM Digi	STM Do3 tal Output NP)	Ao1 Analog Output		MOSI PI


<PRG port>

Note) GND of Di. Do. STM-Di. Do. Ai. Ao. SPi and SG are connected.

Sig 3.3V SV Passive in SWCLK GND SWDIO NRST SWO in out STLINK

Connection side Harness side -Housing 6-pin: SHR-06V-S or SHR-06V-S-B -Contact: SSH-003T-P0.2-H AWG32...28

<GPIO>[Internal] RasPi GPIO40pin (same layout as Raspberry Pi 40pin BM40B-SRDS-G-TF)



The GPIOs of CM4 are 3.3V level. The total GPIO load is up to 50mA. For detailed specifications, please check the CM4 datasheet

MICA-R4 Multi IO IP20



<led></led>			<an< th=""><th>IT SMA port> [O</th><th>ption]</th><th></th><th></th><th></th></an<>	IT SMA port> [O	ption]			
LED	Sts.	Comments	Туре	9	1	ANT2	ANT1	ANT0
P(GR)	Off	No power supply	Wire	d LAN		-		
	On	Power OK	Wire	d LAN+LTE		-		Main
A0(OR)	Blink	E0 active	Wire	d LAN+Wireless LAN	I	-		WL/BT
A1(OR)	Blink	E1 active	Wire	d LAN+Wireless LAN	I+LTE	-		None
Pi(RD)	Off	WD Normal	<cs< td=""><td>I>[Internal] E</td><td>PC conne</td><td>ctor</td><td></td><td></td></cs<>	I>[Internal] E	PC conne	ctor		
	On	WD Error		. [4		
Pi(GR)	Off	User OFF	No.1					
	On	User ON						
Di0,1	Off	Di OFF	Pin	Signal	Pin		Signal	
	ON	Di ON	1	GND	9	_	1_C_P	
Do0,1	Off	Do OFF	2	CAM1_D0_N	10	GND		
	On	Do ON	3	CAM1_D0_P	11	CAM	_GPIO	
USR	Off	User On/Off	4	GND	12	NC		
	On		5	CAM1_D1_N	13	12C1	_SCL[GP	O45]
	On		6	CAM1_D1_P	14	12C2	_SDA[GP	IO44]
	U-1		7	GND	15	3.3V		
			8	CAM1_C_N	16-30	NC		

Device List

Main board side device

Signal	Device	Port or connection	Comments		
E0:GLAN	CM4	eth0	10/100/1000Mbps		
E1:FLAN	LAN9514i	eth1	10/100Mbps		
Security IC	ATECC508A	i2c-0/0x60	i2c0: GPIO0,1		
(option)					
RTC	DS3231SN	i2c-0/0x68	i2c0: GPIO0,1		
OPT:i2c	CM4/GPIO0,1	i2c-0/	i2c0: GPIO0,1		
OPT:RS-232	MCP2200-I	ttyACM1	3-wire, max. 250kbps		
OPT:RS-485	MCP2200-I	ttyACM1	2-wire, max. 400kbps		
CSI:i2c	CM4/GPI44,45	GPIO44,45/i2c-1	i2c1: GPIO44,45 / when not using WD		
CSI	CM4/CAM1	CAM1	MIPI CSI-2 2-lanes		
WD Enable	MAX6373KA+T	GPIO44/Out	SET0 (SET1: Always High, SET2: Always Lov		
WD Reset	MAX6373KA+T	GPIO45/Out	WDI		
* 11-4			Therefore it does not re-dist with MOD4700		

* Not recognized at i2c bus speed of 400kHz or higher. Therefore, it does not conflict with MCP4728

IO expansion board side device							
Signal	Device	Port/Address	Comments				
Di0Di15	MCP23S17	spidev1.0/0	Lower board				
Do0Do7	MCP23S17	spidev1.0/1	Lower board[1.1/0JP selectable]				
Reserve		spidev1.1	Lower board				
Ext.SPI		spidev1.2	Upper board				
CAN0	MCP2518FD	spidev0.0:can0	Lower board				
CAN1	MCP2518FD	spidev0.1:can1	Lower board				
Ai0Ai3	ADS1115	i2c-1/0x48	Upper board[CSI i2c-3/0x48]				
Ao0Ao1	MCP4728	i2c-5/0x60	Upper board[i2c-0 JP selectable]				
RTC,NVRAM*1	MCP74910	i2c-5/0x57,6F	Lower board				
RS-232/485	TXD1,RXD1	ttyAMA0	Lower board RS232 3w Max.250kbps				
			RS485 2w Max.500kbps				
STM32 VCOM	STM32-VCOM	ttyACM0	Upper board Max.921.6kbps[vcom]				
STM32 DIO*2	STM GPIO		Upper board				


*1 When using RTC on the Raspberry Pi OS side, NVRAM cannot be connected on the Codesys side *2 The default protocol to access IO and LED of STM32 is ModbusRTU.

STM32 ModbusRTU link map (slave address 1)

<digital holding="" input="" modbus="" register=""></digital>						
memory offset STM32 Link word/bit						
0/07(unused815) Di0 Di7						
19/015	Reserved					


11000 1)						
<digital holding="" modbus="" output="" register=""></digital>						
memory offset STM32 Link word/bit						
10/03(unused415) Do0 Do3						
11/01(unused215)	LED Red, Green					
1219/015	Reserved					

Optional accessories



Internal DIP switch setting

The board on the left side of MCIA-R4 is the IO board. Only the lower board is mounted on the DIO model. Analog range and serial communication can be selected by switching the switch




Upper board (DIO model is not mounted) >**************** SW2 SW9 SW6 SW3 SW5 SW4

Swite	Switch setting list				
SW	Name	Setting			
SW1	STM32 Reset	OFF*:Invalid ON:Valid			
SW2	STM3 Boot0	OFF:Invalid ON*:User Flash			
SW3	Do Sig. select	OFF*:PushPull High 0.1A ON:Highside Low0.5A			
SW4	Ai0	OFF:0-10VDC ON*:0-5VDC			
SW5	Ai1	OFF:0-10VDC ON*:0-5VDC			
SW6	Ai2	OFF:0-10VDC ON*:0-5VDC			
SW7	Ai3	OFF:0-100VDC ON*:0-5VDC			
SW8	Ao0	OFF:0-10VDC ON*:0-5VDC			
SW9	Ao1	OFF:0-10VDC ON*:0-5VDC			
		* : Default configuration			

Optional accessories

SW1

Optional ac	cessories	Part Number		
PWR	M8 A-code	;	21348100489010	
cable	4-pin fema	le to open end	2m	21348100489020
E1[FLAN]	M8 A-code	4 pin male	1m	72M8M4RM4010LI
cable		to RJ45 Plug	2m	72M8M4RM4020LI
		to RJ45 Jack	0.2m	72T17001449
OPT	M5 4-pin m	nale to open end	1m	72M5M4010G0
cable			2m	72M5M4020G0
E0[GLAN]	ix plug to	to RJ45 Plug	1m	33480653830010
ix cable			2m	33480653830020
		to RJ45 Jack	0.2m	72T17001450IX
Mount	DIN rail mo	ount adapter		20952000004
kit	wall mount	kit		20953000007
Antenna	LTE mono	pole antenna IP20		72MICA0000254
fot LTE	SMA screv	V		
	LTE flat an	itenna IP67		72MICA0000225
	mounted o	n glass or plastic		
	LTE magn	etic mount antenna I	72MICA0000252	
	mounted n	nagnetically on a me		
	3-in-1 ante	nna IP67	72MICA0000255	
	GPS+2x40	S MIMO		
	mounted o	n glass or plastic		



All data given are in line with the actual state of art and therefore not binding HARTING reserves the right to modify designs without giving the relevant reasons.

and you will not be able to use it.

L LTE

MICA-R4 SENSOR IP65



Picture




Product Specifications

Processo	r	Broadcom BCM2711, Quad core @ 1.5GHz				
Memory		RAM4GB, eMMC32GB (Depend on model)				
os		Raspberry Pi OS				
Interface	Front	1x PWR :Power input, 2-line				
		1x LAN : FLAN 1ch				
		1x OPT*1 : i2c/RS-232/485 selectable				
		1x USB : PushPull USB2.0 Host Type-A				
		4x SENSOR1/2/3/4: M8 8pin				
		[Option]1x WLAN IEEE 802.11 b/g/n/ac				
		Bluetooth 5.0, BLE				
		[Option]1x LTE(M.2 slot/EM7431)				
	Back	1x USB-C : USB Type-C(eMMC writing only)				
		1x SW : eMMC write switch				
		1x microSD : microSD slot				
	Internal	1x M.2 slot B-key*2, 1x nanoSIM slot				
		1x CSI, 1xGPIO 40p				
LED, Button		P: Power status, A0,1: LAN status				
		Pi: User custom/WD error				
RTC/NVF		BR1225[or CR1225] Backup RTC				
Watchdo	g	Built-in hardware watchdog				
Power/		GPIO:DC10.7V28.8V/				
Consump		12.5W(incl. USB 500mAx1)				
Tempera	ture	Operating Temp.: -20~60°C, Storage:-25~85°C				
Humidity		Operating Humi.:0~95%(non-condensing)				
IP grade		IP65				
housing r		Aluminum powder coating				
Dimensions		W132 x D89 x H35 mm (excluding protrusions)				
Weight		Approx.610g				
Vibration	/shock	IEC 60068-2-6 / IEC 60068-2-27				
EMI		Radiated emissions EN55016-2-3				
EMS		Electrostatic radiation immunity EN 61000-4-2				
		Radio frequency electromagnetic fields EN 61000-4-3				
		Fast transient burst EN 61000-4-4				
Installatio	n method	DIN rail mounting, wall mounting(Option)				

^{*&#}x27;When WiFi/Bluetooth or LTE options are selected, the OPT connector is replaced to an SMA connector for the antenna.


Details of each part



Features


- Industrial Raspberry Pi 4(CM)
- New processor, up to 2x faster than CM3
- Raspberry Pi OS compatible (Ubuntu requres 4GB or more RAM)
- DC12/24V power input
- Wide operating temperature range and high noise resistance
- M8, M5 connectors with high vibration resistance and connection reliability
- Robust aluminum die-cast housing
- Supports wall mount and DIN rail mount
- On-board eMMC (SD card is not used for boot)
- microSD slot for data storage
- M.2 slot inside SSD and WWAN expansion
- Raspi40p connector for expansion board
- Built-in battery backup RTC
- Highly reliable hardware watchdog

Interface



ODT						Change OPT connector to SIVIA	connector
OPT connector	r Pin	Col.	i2c	RS232	RS485	Туре	OPT
12	1	BR	3.3V/5	V/none*		Wired LAN	
4 (00) 3	2	WH	SCL	TXD	Α	Wired LAN+LTE	Main
+ (00)	3	BL	0V(RS	232:SG)		Wired LAN+Wireless LAN	WL/BT
M5	4		SDA	RXD		Wired LAN+Wireless LAN+LTE	
4pin Female *	1 pin for	power	output is	no output l	by default.	Note) When wireless LAN or LT	E is selected
Sensor						the waterproof performance of the and antenna is different from IP	ne an i port 65.







8 GNDD (Digital GND)

LED	Sts.	Comments
P(GR)	Off	No power supply
	On	Power OK
A0(OR)	Blk	E0 active
A1(OR)	Blk	E1 active
Pi(RD)	Off	WD Normal
	On	WD Error
Pi(GR)	Off	User OFF
	On	User ON

Dimension



Ordering information



^{*2}Not a full pin connection. USB2.0, PCIe, SIM are connected.

MICA-R4 optional accesories

Power cable

Power cable	Part Number		
	1m	21348100489010	
M8 A-coded, 4pin, Femaleopenend	2m	21348100489020 [STD stock]	
openend	5m	21348100489050	

OPT cable



Option port cable		Part Number	
	1m	72M5M4010G0	
M5 4pin, Male openend	2m	72M5M4020G0 [STD stock]	
	5m	72M5M4050G0	

PushPull USB cable



for MICA-R4 IP65 model PushPull USB port

PushPull USB cable	Part Number	
D	1m	09 45 445 1911
PushPull USB 2.0A standard USB 2.0Type-A	2m	09 45 445 1913 [STD Stock]
standard GGB 2.01ypc-A	5m	09 45 445 1915

Sensor cable cor MICA-R4 SENSOR





sensor cable		Part Number
M8, 8pin, Male openend		72T17000113
extention cable for sensor cable		Part Number
M8, 8pin, Male - M8, 8pin, Female	3m	72T17000130
	8m	72T17000131

Dust cap

Dust cap for M5, M8, M12 connector	Part Number
for M8 Male (PWR)	72MICA0000033
for M8 Female(E1, sensor model S1~S4)	72MICA0000034
for M5 Female(OPT, BASIC Plas IP65 model's IO port)	72MICA0000035





Installation adapter	Part Number
DIN-rail mount adapter	20952000004
Wall mount kit	20953000007

DIN rail mout






Startup power supply kit



MICA-R/MICA-R4 General Startup Power Supply Kit	Part Number
DC24V AC adapter + DC jack	72MRPOWK01

LAN cable

- E1 port (FLAN)



		10. 24.01.01.01(2.1)po. 0
LAN cable		Part Number
M8 A-coded, 4pin, Male RJ45 plug	1m	72M8M4RM4010LI
	2m	72M8M4RM4020LI [STD stock]
	5m	72M8M4RM4050LI





- E0 port (GLAN) connect to EO port

30.1 (02)	connect to EO port		for RJ45 cable	
	LAN cable		Part Number	
A plua	D ME inch	0.2m	72T170014E0IV	

PushPull protection cover





PushPull protection cover	Part Number	
Short type	09 45 845 0009	
Long type	09 45 845 0015	
Easy cap (refer to p41)	72PPCAP01	

LTE antenna

LTE antenna		Part Number	
LTE monopole antenna IP20		72MICA0000254	
LTE flat antenna P67 1m		72MICA0000225	
LTE magnetic mount antenna IP65 2m		72MICA0000252	
LTE 3-in-1 antenna (GPS + 2x4G MIMO) IP67	2m	72MICA0000255	





cable 1m LTE 3-in-1antenna LTEmagnetic mount antenna mounted magnetically on a mounted on glass or plastic

metal surface cable 2m

cable 2m

LTE flat antenna

mounted on glass or plastic

CUSTOM

Examples of the latest Al utilization

By installing machine learning/deep learning libraries on MICA-R, cutting-edge AI algorithms can be used for fault diagnosis. HARTING supports customers from the selection of the latest algorithms based on the data collected by MICA-R to the visualization of AI diagnosis results.

- PCA (principal factor analysis) method

Define new features that can be visualized by dimensionality reduction that maximizes the differences between samples.

- Hotelling T2 method


Using a multivariate analysis method, after normalizing a large number of feature values, the Mahalanobis distance is comprehensively evaluated.

- 1-class SVM/Deep SVDD method

Define clusters of normal values using support vectors common in machine learning classifiers.

-Autoencoder method

We define an encoder/decoder that transforms the original data to a lower dimension and restores it by inverse transform, and tune the NN to minimize the loss.




Customize board

The optimal solution for short development periods, low development costs, and unpredictable quantities. Using the Raspberry Pi core module, we develop a carry board that meets the customer's specifications. The Raspberry Pi is an ultra-compact single-board computer (SBC) and is used all over the world, not only in related products and books, but also in many program codes published on the Internet, making it easy for beginners to get started.

Full custom solution

The best solution for long supply periods, high volumes, and when dedicated hardware or special driver designs are required. In this case, we consistently provide an ARM-based embedded Linux board computer that meets customer specifications, from prototype development to the mass production phase, as well as driver, firmware, and software development.



The first steps of shop floor IoT wireless sensing

The need for wireless is also increasing in IoT projects on the manufacturing floor. In particular, wireless sensors greatly reduce installation costs, and the synergistic effect of low-cost general-purpose microcomputers and MEMS sensor chips lowers the threshold for introducing predictive diagnosis IoT. In the IoT of social infrastructure, information from sensors and onsite equipment is often uploaded to cloud servers in the Internet space, but at manufacturing sites, the destination of sensor data is generally the local network for control systems and diagnostic systems. WiFi, Bluetooth, Zigbee, etc. are famous for on-premises (on-site) wireless technology, but due to the availability of bands, propagation characteristics, and power consumption, the sub-giga band known as LoRa (915 MHz in Japan, 866 MHz in Europe, 920 MHz in the United States) is selected in many projects.


Building wireless sensor network

HARTING's wireless sensor communication using the sub-giga band implements a unique modulation method on a wireless chip from Semtech, Inc., and achieves a communication speed of nearly 300kbps (reaching distance of 100m), which is more than 10 times that of LoRa. If you want to focus on distance, you can also transmit up to 10km or more by selecting LoRa modulation.

A USB wireless receiver rMICA-master is connected to an industrial Raspberry Pi as a master device, and communicates with a wireless sensor box that corresponds to a slave device connected to a sensor. It is possible to place multiple wireless sensor boxes (slave units) for one master receiver. The number of wireless sensor boxes is limited by the amount of data sent from the box and the transmission interval. The wireless module also supports multi-hop, so it is possible to relay a USB-connected wireless receiver between parent and child (in that case, a Raspberry Pi is not required, but a 5V power supply is required).

The sub-giga band (915-930MHz) is a frequency band allocated by the Ministry of Internal Affairs and Communications in 2010 mainly for wireless sensors and UHF RFID tag communication. Some channels are also shared by UHF RFID tags, so please check the radio wave usage status. Multiple sensor networks can be constructed in the same area by selecting different channels.

rMICA



rMICA Product List



USB wireless base station rMICA-master Base station for communicating with the wireless sensor box



Wireless sensor box
MICA-vibration
Process measurements from accelerometer probes
Transmitted wirelessly to host computer


USB wireless base station

rMICA-master



A base station for communicating with the wireless sensor box. connect to a host computer such as MICA-R via USB.

- Built-in 920MHz wireless module
- Industry's fastest transmission speed of 300kbps by adopting wireless chip manufactured by Semtech in the United States.
 (200m) achieved.
- Compatible with frequency bands around the world (requires radio certification separately)
- USB power supply
- Dustproof and waterproof IP65





Product specifications

Model name	rMICA-master
main chip	FTDI FT234XD-R、SEMTECH SX series
Interafce	M8 4pin male x 1: USB2.0A RMA female x 1: external antenna
Power	Not required (USB power supply)
IP class	IP65
Certification	TELEC(Wireless)
Wireless standard	Domestic 920MHz band sub-giga standard
wireless chanel	24 (916MHz) ~ 61 (928MHz)
Wireless output (module)	20mW
Antenna	Omnidirectional 3dBi, RMA male
Host cnnection	USB 2.0 A
Housing	Flame-retardant ABS
Operating temp. range	-15 60° C
Size WxHxD(mm)	100 x 24.5 x 59
Mounting	4 x M4 screws

Oder information

Main unit

Model	Part Number
USB wireless base station rMICA-master	72RMICAMSTR01

USB cable

USB cable (MICA-R4 or general PC connection)	Part Number	
M8 A-coded, 4pin, Female USB 2.0A [aux.]	Please contact us	
USB cable (MICA-R4, waterproof)		Part Number
M8 A-coded, 4pin, FemalePushPull USB 2.0A	2m	Please contact us






Wireless sensor box for acceleration sensor


rMICA-vibration



It processes the readings from the accelerometer probe and wirelessly sends them to the host computer

- Super power saving microcomputer STM32L4 adopted
- · Industry's fastest transmission speed of 300kbps by adopting
- a wireless chip manufactured by Semtech in the United States (200m) achieved.
- · Compatible with frequency bands around the world (requires radio certification separately)
- · Battery drive, built-in high-capacity long-life battery
- · Dustproof and waterproof IP65





(unit:mm)

Product specifications

Model name	rMICA-vibration
main chip	STM32 L432K、SEMTECH SX series
Interafce	M8 8pin Female x 1: sensor input RMA Female x 1:external antenna
Power Built-in battery: 3.6 V, 13.5 Ah	
IP class	IP65
Wireless standard	Domestic 920MHz band sub-giga standard
wireless chanel	24 (916MHz) ~ 61 (928MHz)
Wireless output (module)	20mW
Antenna	Omnidirectional 3dBi, RMA male
Housing	Flame-retardant ABS
Certification	TELEC(Wireless)
Operating temp. range	-15 60° C
Size WxHxD(mm)	122 x 31 x 69.5
Mounting	4 x M4 screws

Oder information

Main unit

Model	Part Number	
Wireless box for acceleration sensor rMICA-vibration	72RMICAVIBR01	

Accessories

Model	Part Number	
Battery for acceleration sensor wireless sensor box	72RMICABATRO1	

Analog voltage output 0-10kHz 1-axis acceleration sensor **SMICA-ACC**



DC current sensor sMICA-CUR



High-precision measurement of vibrations of motors etc., using high-performance MEMS sensors


- Measuring range over 20,000 Hz by adopting the latest MEMS chip Achieves overwhelmingly low noise
- Suitable for motor failure diagnosis
- Built-in temperature sensor (I2C) and low
- speed 3-axis acceleration sensor (I2C)
- Dustproof and waterproof IP66
- Industrial Raspberry Pi MICA-R STM32 SENSOR or Used by connecting to the wireless sensor box rMICA-vibration

Product specifications

- 1	Model/Part Number	sMICA-ACC / 72SMICAACC	
		Mounting method	M6 screw
probe		Operating temp. range	-20 85° C
		IP rating	IP66
		Material	Hard anodized
		Size	φ21.3 x 33.4mm
		Size	(excl. protrusions and cables)
	Attached cable	Length	2m
	Attached cable	Connector	M8 8pinMale
		Acceleration range	-10g+10g
		Frequency range	010kHz(±10%)
	1 axis	Noise level	25µg/√Hz
	Acceleration sensor	Nominal sensitivity	40mV/g
	(analog voltage output))	Sensitivity due to temp.	±2%
		Linearity error	0.1%FS
		Cross-axis sensitivity	-1+1%
ф		Supply voltage	5V
Built-in	temperature sensor	Temp. sensor range	-40125°C
		Temp. sensor accuracy	±3° C(-40 ~ 85° C)
sensor	(I2C output)	Resolution	10bits
sn		Supply voltage	3.3V
윽		Acceleration range	2~16g
		Sample rate	1Hz
	low speed 3 axis	Resolution	10bits
	Acceleration sensor	0g offset error	— 250 ~ 250mg
	(I2C output)	0g offset temp. coefficient	±1.2mg/° C
	(120 output)	Linearity error	±0.5%FS
		Cross-axis sensitivity	-1+1%
		Supply voltage	3.3V

Probe dimensions

M8 connector cable details



Compact, space-saving, low-cost current sensor


- -Space-saving design with a width of 25.9 mm
- -Separate type for easy retrofitting
- -DC30A φ10mm
- -Response performance of 10µsec or less at 0 \rightarrow rated current
- -Easy-to-use +5V single power supply specification

Product specifications

Model/Part Number	sMICA-CUR / 72MICACTF3010DC
Rated current	DC 30A
Allowable current	DC 33A
Output voltage	+30A input : DC +4.5V 0Ainput : DC +2.5V -30A input: DC +0.5V
Attachable wire diameter	Max.φ10mm
Accuracy	±2.0%F.S
Temp. coefficient	±0.1%/°C
Response speed	0 → 10 µsec or less at rated current
Power supply voltage	+5V±5%(Single power supply)
Withstand voltage	AC 2000V/1min(Outer case - Output)
Insulation resistance	DC 500V/100MΩ以上 (Outer case - Output)
Operating temp./humi. range	-10 ~ 65℃ / Less than 85%RH(No condensation)
Reference standard	RoHS
cable	20cm (connector : M8 8pin male)
Wiring	Red: Power +5V White: Output OUT Shield: Power 0V/Output GND
Size / Weight	W25.9×H65.2×D31.1mm / approx.36g

Dimensions

M8 connector wiring





Pin	Wiring				
1	NC				
2	Red: Power+5V				
3	White: Output OUT				
4	Shield: Poweer0V • Output GND				
5	NC				
6	NC				
7	NC				
8	NC				

cable length about 20cm M8 8-pin male connector included



Raspberry Pi ready for industrial use

The RevPi series is an industrial Raspberry Pi that is equipped with an embedded Raspberry Pi Compute Module (CM) and can be easily introduced at a low cost. As a computer that can be easily attached to a control panel with a DIN rail, it is ideal for applications such as traceability data collection, linkage with PLCs, and digital signage (displaying information on a large screen). It is in actual operation on automobile manufacturing lines and machine tools.





New RevPi S/SE series with CM4S

The previous RevPi was equipped with CM3+, which is equivalent to the general Raspberry Pi 3B+, but the new RevPi S series / SE series equipped with CM4S based on the same ARM Cortex-A72 processor as the latest CM4 has appeared. The form factor of CM4S has not changed from CM3+, the clock has been improved from 1.2GHz to 1.5GHz, and the RAM has been enhanced from LPDDR2 to LPDDR4.









Compare main specifications

Model	RevPi Core 3+	RevPi Connect+	RevPi Core S/SE	RevPi Connect S/SE	
Compute Module	CM3+		CM4S	E	
Processsor	Broadcom BCM2837B0, quad-core ARM Cortex-A53		Broadcom BCM2711, quad-core ARM Cortex-A72		
Clock rate	1	2 GHz	1.5 GHz		
RAM	1 G	B LPDDR2	1 GB	LPDDR4	
eMMC Flash memory	8 GB / 1	16 GB / 32 GB	8 GB / 1	6 GB / 32 GB	
HDMI version	HDM	I 1.3a (FHD)	HDM	12.0a (4K)	
Power	12 - 24 V DC				
RJ45 LAN port (10/100Mbit/s)	1	2 (separate MAC addresses)	1	2 (separate MAC addresses)	
USB2.0	2	2	2	2	
microHDMI	1	1	1	1	
microUSB2.0(for eMMC writing)	1	1	1	1	
RS-485(4-pin terminal connector)		1	-	1	
PiBridge(I/O exp.module,Gate module)	2	1	2	1	
ConBridge(RevPi Con module)		1		1	
UPS shutdown signal 24V input		1		1	
Programable relay switch contact		1	323	1	
Size (D x W x H)	110.5 x 22.5 x 96 mm	110.5 x 45 x 96 mm	110.5 x 22.5 x 96 mm	110.5 x 45 x 96 mm	
IP rating	IP20				
ESD protection	4 kV/8 kV				
EMI (acc. to EN61131-2 and IEC61000-6-2)	Passed				
Surge/Burst(acc. to EN61131-2 and IEC61000-6-2)	Passed				
CE, RoHS	Yes				
UL	Yes, UL-File-No. E494534				

RevPi Core S / Connect S



Compute Module 4S installed, onboard eMMC8/16/32GB, fieldbus module compatible

RevPi Core S



Product Specifications

•	
Powered by Raspberry Pi	Compute Module 4S (CM4S)*
Processor	Broadcom BCM2711,
	Quad-core Arm Cortex-A72, 1.5GHz
RAM	1GB LPDDR4
Flash	Onboard eMMC 8/16/32GB
OS	Raspberry Pi OS
Interface	1 x power input connector
	2 x USB Type-A (max. current up to 900mA for both)
	1x RJ45 10/100Mbps Ethernet
	1 x Micro-USB (only for image transfer to eMMC)
	1 x Micro HDMI : HDMI 2.0a (4K)
Expansion interface	2 x PiBridge system bus (black)
	Connectable expansion modules**:
	RevPi IO Module and RevPi Gate Module
LED	PWR normal (green), abnormal (red)
	A1, A2 custom enabled LEDs (green/red)
Power input range	DC12-24V -15%/+20%
Power consumption	about 10W
Operating temp. range	-25 55°C
Storage temp. range	-40 85°C
Operating humidity range	93% (no condensation)
Degree of protection	IP20
Housing material	Polycarbonate
Dimensions	H96 x D22.5 x W110.5mm (excluding protrusions)
weight	Approx. 115g
ESD protection	4kV / 8kV (EN61131-2, IEC61000-6-2)
EMI	EN61131-2, IEC61000-6-2
Surge/burst	EN61131-2, IEC61000-6-2
Certification	CE, RoHS
RTC buffer time	min.24h
Installation method	DIN rail mounting
Add-on Software	Software PLC CODESYS pre-installable

^{*}Please note that CM4S new CPUs are only supported with kernel 5.10.

 Optional accessory RevPistart up power kit (AC adopter + Connector) [Part Number : 72PRPOWK01]



Ordering information

Model	CODESYS	eMMC	Part Number
		8GB	72PR100359
	not-installed	16GB	72PR100360
RevPi Core S		32GB	72PR100361
nevel cole 5		8GB	72PR100359C01
	pre-installed	16GB	72PR100360C01
		32GB	72PR100361C01

RevPi Connect S



Product Specifications

Powered by Raspberry Pi	Compute Module 4S (CM4S)*
Processor	Broadcom BCM2711,
1 1000001	Quad-core Arm Cortex-A72, 1.5GHz
RAM	1GB LPDDR4
Flash	Onboard eMMC 8/16/32GB
OS	Raspberry Pi OS
Interface	1 x power input connector
	1 x digital input/output connector
	Input: 24V input, about 3.0V (0->1)/2.3V (1->0)
	Relay output: 2A @ DC30V (resistive load)
	2 x USB Type-A (max current up to 1A for both)
	2 x RJ45 10/100 Mbps Ethernet (separate MAC)
	1 x RS-485 connector (without electrical isolation)
	1 x Micro-USB (only for image transfer to eMMC)
	1 x Micro HDMI : HDMI 2.0a (4K)
Extended	1 x PiBridge system bus (black)
interface	1 x ConBridge system bus (grey)
	Connectable expansion modules**:
	RevPi IO Module, RevPi Con Module,
	and RevPi Gate module
LED	PWR normal (green), abnormal (red)
	A1, A2, A3 Custom usable LEDs (green/red)
	WD Watchdog normal (green), abnormal (red)
	REL relay output status on (green), off (light off)
Power input range	DC12-24V -15%/+20%
Power consumption	about 20W
Operating temp. range	-25 55°C
Storage temp. range	-40 85°C
Operating humidity range	93% (no condensation)
Degree of protection	IP20
Housing material	Polycarbonate
Dimensions	H96 x D45 x W110.5mm (excluding protrusions)
Weight	Approx. 224g (including connector)
ESD protection	4kV / 8kV (EN61131-2, IEC61000-6-2)
EMI	EN61131-2, IEC61000-6-2
Surge/burst	EN61131-2, IEC61000-6-2
Certification	CE, RoHS
RTC buffer time	min.24h
Installation method	DIN rail mounting
Add-on Software	Software PLC CODESYS pre-installable

Ordering information

Model	CODESYS	eMMC	Part Number
		8GB	72PR100362
	not-installed	16GB	72PR100363
RevPi Connect S	pre-installed	32GB	72PR100364
nevel Connect 5		8GB	72PR100362C01
		16GB	72PR100363C01
		32GB	72PR100364C01

^{**} RevPi Core S can use his IO expansion module for digital/analog input/output expansion and Gate module for fieldbus.

^{*}Please note that CM4S new CPUs are only supported with kernel 5.10.

** RevPi Connect S can use his IO expansion module for digital/analog input/output expansion,
Con module for M-bus/CAN-bus and Gate module for fieldbus.

RevPi Core SE / Connect SE



Compute Module 4S installed, onboard eMMC8/16/32GB

RevPi Core SE




Product Specifications

Powered by Raspberry Pi	Compute Module 4S (CM4S)*
Processor	Broadcom BCM2711,
	Quad-core Arm Cortex-A72, 1.5GHz
RAM	1GB LPDDR4
Flash	Onboard eMMC 8/16/32GB
os	Raspberry Pi OS
Interface	1 x power input connector
	2 x USB Type-A (max.current up to 900mA for both) 1x RJ45 10/100Mbps Ethernet
	1 x Micro-USB (only for image transfer to eMMC) 1 x Micro HDMI : HDMI 2.0a (4K)
Expansion interface	2 x PiBridge system bus (black)
Expansion interface	Connectable Expansion Modules**: RevPi IO Module
LED	PWR normal (green), abnormal (red)
	A1, A2 custom enabled LEDs (green/red)
Power input range	DC12-24V -15%/+20%
Power consumption	about 10W
Operating temp. range	-25 55°C
Storage temp. range	-40 85°C
Operating humidity range	93% (no condensation)
Degree of protection	IP20
Housing material	Polycarbonate
Dimensions	H96 x D22.5 x W110.5mm (excluding protrusions)
weight	Approx. 115g
ESD protection	4kV / 8kV (EN61131-2, IEC61000-6-2)
EMI	EN61131-2, IEC61000-6-2
Surge/burst	EN61131-2, IEC61000-6-2
Certification	CE, RoHS
RTC buffer time	min.24h
Installation method	DIN rail mounting
Add-on Software	Software PLC CODESYS pre-installable

^{*}Please note that CM4S new CPUs are only supported with kernel 5.10.

 Optional accessory RevPistart up power kit (AC adopter + Connector)
 [Part Number: 72PRPOWK01]



Ordering information

Model	CODESYS	eMMC	Part Number
		8GB	72PR100365
	not-installed	16GB	72PR100366
RevPi Core SE	pre-installed	32GB	72PR100367
nevel cole SE		8GB	72PR100365C01
		16GB	72PR100366C01
		32GB	72PR100367C01

RevPi Connect SE



Product Specifications

Powered by Raspberry Pi	Compute Module 4S (CM4S)*	
Processor	Broadcom BCM2711,	
	Quad-core Arm Cortex-A72, 1.5GHz	
RAM	1GB LPDDR4	
Flash	Onboard eMMC 8/16/32GB	
OS	Raspberry Pi OS	
Interface	1 x power input connector	
	1 x digital input/output connector	
	Input: 24V input, about 3.0V (0->1)/2.3V (1->0)	
	Relay output: 2A @ DC30V (resistive load)	
	2 x USB Type-A (max current up to 1A for both)	
	2 x RJ45 10/100 Mbps Ethernet (separate MAC)	
	1 x RS-485 connector (without electrical isolation)	
	1 x Micro-USB (only for image transfer to eMMC)	
	1 x Micro HDMI : HDMI 2.0a (4K)	
Extended	1 x PiBridge system bus (black)	
interface	1 x ConBridge system bus (grey)	
	Connectable expansion modules**:	
	RevPi IO Module and RevPi Con Module	
LED	PWR normal (green), abnormal (red)	
	A1, A2, A3 Custom usable LEDs (green/red)	
	WD Watchdog normal (green), abnormal (red)	
	REL relay output status on (green), off (light off)	
Power input range	DC12-24V -15%/+20%	
Power consumption	about 20W	
Operating temp. range	-25 55°C	
Storage temp. range	-40 85°C	
Operating humidity range	93% (no condensation)	
Degree of protection	IP20	
Housing material	Polycarbonate	
Dimensions	H96 x D45 x W110.5mm (excluding protrusions)	
Weight	Approx. 224g (including connectors)	
ESD protection	4kV / 8kV (EN61131-2, IEC61000-6-2)	
EMI	EN61131-2, IEC61000-6-2	
Surge/burst	EN61131-2, IEC61000-6-2	
Certification	CE, RoHS	
RTC buffer time	min.24h	
Installation method	DIN rail mounting	
Add-on Software	Software PLC CODESYS pre-installable	

^{*}Please note that CM4S new CPUs are only supported with kernel 5.10.

Ordering information

Model	CODESYS	eMMC	Part Number
		8GB	72PR100368
	not-installed	16GB	72PR100369
RevPi Connect SE		32GB	72PR100370
nevel Connect 3E	pre-installed	8GB	72PR100368C01
		16GB	72PR100369C01
		32GB	72PR100370C01

^{**}RevPi Core SE does not support RevPi Gate module for fieldbus.

^{**} RevPi Connect SE can use his IO expansion module for digital/analog I/O expansion, Con module for M-bus/CAN-bus. RevPi Gate module for fieldbus is not supported.

Revolution Pi expansion modules Digital IO modules






Product Specifications

Digital input channel	14ch PNP
Digital input	Insulation: internal logic, DC24V(Device power/output)
Electrical specifications	Input current limitation: 2.4 mA (at 24 V power supply)
	counter input : 2kHz(corresponding to 500Hz encoder)
Digital input connection	14pin socket connectors (0.21.5 mm²)
Digital output channel	14ch PNP
Digital output	Insulation: internal logic, DC24V(Device power/output)
Electrical specifications	Current output : 500mA(High-Side Mode),
	100mA(Push-Pull Mode)
	PWM*: 40/80/160/200/400Hz(selectable)
Digital output connection	14pin socket connectors (0.21.5 mm²)
Alarm	Thermal shutdown or short circuit of outputs(for each output).
Dual	In the event of communication failure with the controller (after
Watchdog	50 ms or 500 ms 4) or internal communication with the CPU (after
	9 ms, hardware-controlled), the outputs are reseted to zero.
Output protection	According to EN 61131-2 (IEC 61000-4-4, -5, -6, and -2) against
	short circuit, overload, burst, ESD.
Power input range	DC12-24V -15%/+20%
Power input protection	Reverse polarity protected, transient overvoltages
Power consumption	1.5 Watt (X4/power supply)
Operating temp. range	-40 55 °C
Storage temp. range	-40 85 °C
Operating humidity range	0 93% (non-condensing)
Degree of protection	IP20
housing material	Polycarbonate
External dimensions	H96 x D22.5 x W110.5mm (excluding protrusions)
weight	approx. 100 g / 130 g (incl. connectors)
Installation method	DIN rail mount
CE, RoHS	Yes

*PWM pulse width is stored in 1 byte in the process image as a value between 0 and 100. The maximum resolution of conversion (%) of this value by the module depends on the PWM frequency (40 Hz/1%, 80 Hz/2%, 160 Hz/4%, 200 Hz/5%, 400 Hz/10%)

Details of parts



Ordering information


Model	Name	Part Number
Digital input 14ch / output 14ch module	RevPi DIO	72PR100197

Dimension




Wiring diagram


Wiring diagram for 3-port isolation method



Wiring diagram for single power supply system



Wiring diagram for single power supply system



Revolution Pi expansion modules Analog IO module






Product Specifications

Analog input channel	6ch
Analog input	for voltage Max.4ch : ±10 V ±5 V 010 V 05 V
Electrical specifications	for current Max.4ch : 020 mA 024 mA 420 mA
	±25 mA
	for RTD (Pt100/Pt1000) Max.2ch : 2/3/4w -200+850 °C
Analog input connection	14pin connector (0.2 - 1.5 mm²)
Analog output channel	2ch
Analog output	for voltage Max.2ch : ±10 V ±11 V ±5 V ±5.5 V
Electrical specifications	010 V 011 V 05 V 05.5 V,
	for current Max.2ch : 020 mA 024 mA 420 mA
Analog output connection	14pin connector (0.2 - 1.5 mm²)
Galvanic isolation	Input to Input : No, Input to Output : Yes,
	Output to Output : No, System bus to inputs/outputs : Yes
Input type	Voltage/current : differential, RTD : 2, 3, 4-wire
Output type	single ended, common ground, short-circuit proof
ADC/DAC	24 bit ΔΣ / 16 bit
Input resolution	Voltage:1mV(16bit),Current:1µA(16bit), RTD:0.1 K(16bit)
Output resolution	Voltage:1mV(16bit), Current:1µA(16bit)
Input accuracy @25°C	Voltage:±10 mV (±5 mV @ 05 V range)
	Current:±20 μA (±24 μA @ 024 μA range)
	RTD :±0.5 K
Output accuracy @25°C	Voltage:±15 mV
	Current:±20 μA
input conversion time	81000 mss (adjustable)
Output slew rate	1 LSB@3.3 kHz up to 128 LSB@258 kHz
input impedance	Voltage:>900 kΩ, Current:<250 Ω
output impedance	Voltage:<16 Ω, Max. capacitive load 5 nF @1 kΩ
Load resistance	Max. load resistance for current output:600 Ω,
	Min. load resistance for voltage output:1 kΩ
Power input range	DC1224V -15%/+20%
Power input protection	Reverse polarity protection, overvoltage protection
Current consumption	Max.200mA/24V(full load), Max.500mA(start up)
Operating temp. range	-3055 °C
Storage temp. range	-4085 °C
Operating humidity range	093%(No condensation)
IP rating	IP20
Housing	Polycarbonate
Size	H96 x D22.5 x W110.5mm (Does not include protrusions)
Weight	approx. 115g(incl. connector)
Installation method	DIN-rail mount
CE, RoHS	Yes


Details of parts

Analog in 6ch/Out 2ch AIO module





RevPi AIO

Dimension




Wiring diagram





Analog output



All data given are in line with the actual state of art and therefore not binding. HARTING reserves the right to modify designs without giving the relevant reasons.

72PR100250

Industrial Raspberry Pi Peripherals 2.0MP, CMOS, USB 2.0 camera



- Maximum resolution: 1920 x 1080
- Video monitoring by plug and play with PC, no additional power supply required
- Reliable function in both high and low light environments
- High-performance Sony IMX322 sensor adopted
- Voice support

Product specifications

Sensor	Sony IMX322
Pixel size	12.8X11.6 mm
Lens size	1/2.9"
Lens parameters	5-50mm, varifocal lens, CS mount
Image area	2000 (H) X1121 (V) Approx. 2.24 M pixels
Resolution	Up to 1920 x 1080P, 2 megapixels
Frame rate	H264: Up to 1920X1080@30fps MJPEG: Up to 1920X1080 @ 30fps YUV: Up to 800X600@15fps
Dynamic range	86dB
SNR	42dB
Sensitivity	5.0 V/lux-sec @ 550nm
Minimum illumination	0.01 lux
Gain	adjustable
Exposure time	adjustable
Shutter mode	Electronic rolling shutter/frame exposure
Data interface	USB2.0 High Speed
Compression method	H264 /MJPEG / YUV2(YUYV)
Power supply	DC5V, USB BUS POWER 4P-2.0mm socket
Temperature	Operating temperature -20 85°C
Size	Board 41 x 41 mm
Weight	About 200g
os	Win7, Win8, Win10 Linux 2.6 or higher Android 4.0 or higher
Cable	USB cable 3m (standard)

Order information

Product name	Part Number
2.0MP, CMOS, USB 2.0 camera	72USBFHD06H-SFV





Construct an image processing application in combination with the RevPi series and $\mbox{MICA-R4}$

Industrial Raspberry Pi Peripherals

Industrial USB hub





- 4-port industrial USB2.0 hub
- 1 x USB Type-B: Upstream
- 4 x USB Type-A: Downstream
- 120...480Mbps
- DC7V to DC24V (power supply connector)
- Support USB bus power (jumper selection)
- Compatible with Windows, Linux, Mac OS
- Compatible with DIN rail mounting (mounting kit included)
- Wide operating temperature range 0°C to +55°C
- Protection class IP30

Product specifications


Part Number	72EX-1163HM
Chipset	NEC uPD720114
Data rate	120480Mbit/s
Support OS	Windows 98SE/ME/2000/ XP/Vista/7/8.x/10(32&64-Bit)/ CE/ Server(2003, 2008 & 2012 R2), Linux, Mac OS 10.x
Connector	4x USB 2.0 Type-A ports 1x USB 2.0 Type-B port 1x DC7V~DC24V 3-pin connector terminal block
Support system	USB 1.1, 2.0, 3.0, 3.1
Power	DC7VDC24V
Operating temp. range	Operating temp. 0 +55°C/Storage temp40 85°C
Operating Humi. range	095%(non-condensing)
IP rating	IP30
Size	114.5 x 66.43 x 26.0 mm
Weight	420g
Accessories	USB cable 2.0m DIN rail mount kit


Details of each part Interface



Connector









Device power supply selection (jumper selection)

The unit supports two types of device power input via internal jumpers.

The factory setting is the jumper "T" side, and the power input is wired on the connector terminal block. Switch the jumper to the "U" side to operate the device with USB bus power from the upstream side. When changing the jumper settings, be sure to remove all wiring, remove the two screws, and open the housing.



Dimensions



Order information

Product name	Part Number
4 port industrial usb hub	72EX-1163HM



www.pi4industry.com

Industrial Raspberry Pi website



www.lintronix.com.tw









台中市南屯區東興路一段500號 TEL: 04-2471-2125 FAX: 04-2471-2124

